

Novell NetWare® 6

www.novell.com

OTHER INSTALLATION OPTIONS



N

Novell®

Legal Notices

Novell, Inc. makes no representations or warranties with respect to the contents or use of this documentation, and specifically disclaims any express or implied warranties of merchantability or fitness for any particular purpose. Further, Novell, Inc. reserves the right to revise this publication and to make changes to its content, at any time, without obligation to notify any person or entity of such revisions or changes.

Further, Novell, Inc. makes no representations or warranties with respect to any software, and specifically disclaims any express or implied warranties of merchantability or fitness for any particular purpose. Further, Novell, Inc. reserves the right to make changes to any and all parts of Novell software, at any time, without any obligation to notify any person or entity of such changes.

This product may require export authorization from the U.S. Department of Commerce prior to exporting from the U.S. or Canada.

Copyright © 1993-2001 Novell, Inc. All rights reserved. No part of this publication may be reproduced, photocopied, stored on a retrieval system, or transmitted without the express written consent of the publisher.

U.S. Patent No. 5,157,663; 5,349,642; 5,455,932; 5,553,139; 5,553,143; 5,572,528; 5,594,863; 5,608,903; 5,633,931; 5,652,859; 5,671,414; 5,677,851; 5,692,129; 5,701,459; 5,717,912; 5,758,069; 5,758,344; 5,781,724; 5,781,724; 5,781,733; 5,784,560; 5,787,439; 5,818,936; 5,828,882; 5,832,274; 5,832,275; 5,832,483; 5,832,487; 5,850,565; 5,859,978; 5,870,561; 5,870,739; 5,873,079; 5,878,415; 5,878,434; 5,884,304; 5,893,116; 5,893,118; 5,903,650; 5,903,720; 5,905,860; 5,910,803; 5,913,025; 5,913,209; 5,915,253; 5,925,108; 5,933,503; 5,933,826; 5,946,002; 5,946,467; 5,950,198; 5,956,718; 5,956,745; 5,964,872; 5,974,474; 5,983,223; 5,983,234; 5,987,471; 5,991,771; 5,991,810; 6,002,398; 6,014,667; 6,015,132; 6,016,499; 6,029,247; 6,047,289; 6,052,724; 6,061,743; 6,065,017; 6,094,672; 6,098,090; 6,105,062; 6,105,132; 6,115,039; 6,119,122; 6,144,959; 6,151,688; 6,157,925; 6,167,393; 6,173,289; 6,192,365; 6,216,123; 6,219,652; 6,229,809. Patents Pending.

Novell, Inc.
1800 South Novell Place
Provo, UT 84606
U.S.A.

www.novell.com

Other Installation Options
October 2001
103-000143-001

Online Documentation: To access the online documentation for this and other Novell products, and to get updates, see www.novell.com/documentation.

Novell Trademarks

Internetwork Packet Exchange and IPX are trademarks of Novell, Inc.

NE2000 is a trademark of a Novell, Inc.

NetWare is a registered trademark of Novell, Inc. in the United States and other countries.

NetWare Loadable Module and NLM are trademarks of Novell, Inc.

Novell is a registered trademark of Novell, Inc. in the United States and other countries.

Novell Client is a trademark of a Novell, Inc.

Novell Directory Services and NDS are registered trademarks of Novell, Inc. in the United States and other countries.

Novell Distributed Print Services is a trademark of Novell, Inc. and NDPS is a registered trademark of Novell, Inc. in the United States and other countries.

Novell Storage Services is a trademark of a Novell, Inc.

SFT and SFT III are trademarks of Novell, Inc.

Third-Party Trademarks

All third-party trademarks are the property of their respective owners.

Contents

Overview	9
Using NetWare Accelerated Upgrade	9
Automating the NetWare Installation with a Response File	9
Using Installation Scripts for NetWare Installation	10
Documentation Conventions	10
1 Using NetWare Accelerated Upgrade	11
How NetWare Accelerated Upgrade Works	11
Upgrading to NetWare 6	13
Prepare the Workstation	13
Prepare a Staging Server.	13
Prepare the Target Server	15
Prepare the Network	17
Run NetWare Accelerated Upgrade	18
Complete Post-Upgrade Tasks	20
Specifying Disk Drivers Manually	20
Troubleshooting Server-to-Server Connections	21
Disabling SAP Filtering	21
Detaching from Unauthenticated Servers	21
Setting the Target Server's Gate Parameter to Its Default Router IP Address	22
2 Automating the NetWare Installation with a Response File	25
Creating a Response File	26
Creating a New Response File	26
Editing a Response File from a Previous Server Installation	26
Using a Response File	27
Using a Response File during a Server Installation	27
Entering a Response File at the Command Line	27
Syntax	28
NetWare Sections and Keys	33
[NWI:Product Information] Section	33
[NWI:Language] Section	34

[NWl:Install Options] Section	35
[NWl:Server Settings] Section	37
[NWl:Locale] Section	38
[NWl:Mouse and Video] Section.	39
[NWl:Hardware] Section	40
[NWl:Excluded From Detection] Section.	44
[NWl:Multi-Processor System] Section	44
[NWl:Storage Adapter <i>n</i>] Section	45
[NWl:Storage Device <i>n</i>] Section	46
[NWl:Network Adapter <i>n</i>] Section	47
[NWl:Reserved Adapter <i>n</i>] Section	50
[NWl:Hotplug System] Section.	50
[NWl:NetWare Loadable Module] Section	51
[NWl:File System] Section	51
[NWl:Partition <i>n</i>] Section.	52
[NWl:Volume <i>n</i>] Section	56
[NWl:Misc] Section.	59
[NWl:File Server] Section	60
[NWl:Protocols] Section	61
[NWl:TCPIP] Section	62
[NWl:IPX] Section	63
[NWl:IPCMD] Section	64
[NWl:SNMP] Section.	65
[NWl:DNS] Section	67
[NWl:Host Name] Section	68
[NWl:Time Zone] Section	69
[NWl:Time Synchronization] Section	70
[NWl:NDS] Section	70
[NWl:License] Section	74
[NWl:Add to Startup] Section	76
[NWl:Append To Autoexec.ncf] Section	77
[NWl:Use NCF Settings] Section	77
Performing a Fully Automated Installation.	78
[Novell:NOVELL_ROOT:1.0.0] Section	78
Automating the Installation of Additional Products and Services	79
[Selected Nodes] Section	80
Installing Multiple Products on a Server	82
Product Keys and Values	82
Additional Services	83
CD Boot and the Response File.	87
Customizing the Installation Using Install Scripts	87
[NWl:Install Script] Section	88
Performing a Factory Install	90
[NWl:Factory] Section	91
[Novell:StartupDirectory:1.0.0] Section	92

[Novell:SYSDirectory:1.0.0] Section	92
[Novell:ConfigDirectory:1.0.0] Section	93
[Novell:LANFiles:1.0.0] Section.	93
[Novell:SBDFiles:1.0.0] Section	94
[Novell:portalzip:1.0.0] Section	94
[Novell:Rconjzip:1.0.0] Section	95
[Novell:Perl5zip:1.0.0] Section	95
[Novell:beanszip:1.0.0] Section.	96
[Novell:nscriptzip:1.0.0] Section	96
[Novell:scripteszip:1.0.0] Section	97
[Novell:console1zip:1.0.0] Section	97
[Novell:ldapzip:1.0.0] Section.	98
[Novell:wanmanzip:1.0.0] Section	98
Install Command Line Options	99

3 Installation Scripts for NetWare 101

Using NetWare Installation Scripts.	101
Script Files	101
Launching a Script File	102
Using a Script with NetWare 6	102
Descriptors and Commands	103
Syntax Conventions	103
Comments	104
Descriptors	104
Commands	120
External Commands	125
Version 2.10 External Command Compatibility.	125
External Command Syntax	126
Commands	126
External Command Programming Interface	154
ICMDSetVar	154
ICMDGetVar	155
External Command Variable Substitution	156
Example	157
Installation NLM Command Line Options	158
User-Documented Switches for NetWare Installation	158
Switches Helpful for Install Script Writers	158
Other Switches	159
NetWare 4.1 Remote Installation Wrapper.	160
NetWare Installation Command Version Availability	161
NetWare Install Commands	161
NetWare External Install Commands.	162

Overview

The following advanced options can help you upgrade or install NetWare® servers.

Using NetWare Accelerated Upgrade

You can run NetWare Accelerated Upgrade from a Windows* client workstation, so that you don't need to be physically present at the server console. Although NetWare Accelerated Upgrade is quicker than the standard installation process, it does not install additional network products, licensing services, or license certificates.

See [Chapter 1, “Using NetWare Accelerated Upgrade,”](#) on page 11.

Automating the NetWare Installation with a Response File

Installing the NetWare operating system software can be easier and more flexible when you use a response file. When used with the graphical server installation, a response file lets you

- ♦ Set and display specific defaults
- ♦ Bypass entire sections of the installation
- ♦ Automate the entire server installation process

A response file is a text file containing sections and keys (similar to a Windows .INI file). You can create a response file using any ASCII text editor. If you use a response file, the NetWare server installation reads the installation parameters directly from the response file, replacing the default installation values with response file values.

See [Chapter 2, “Automating the NetWare Installation with a Response File,”](#) on page 25.

Using Installation Scripts for NetWare Installation

NetWare installation scripts let you

- ♦ Alter or extend the NetWare installation process
- ♦ Install additional products or services on a NetWare server after the operating system has been installed

See [Chapter 3, “Installation Scripts for NetWare,”](#) on page 101.

Documentation Conventions

In this documentation, a greater-than symbol (>) is used to separate actions within a step and items in a cross-reference path.

Also, a trademark symbol (® , ™, etc.) denotes a Novell trademark. An asterisk (*) denotes a third-party trademark.

1

Using NetWare Accelerated Upgrade

The NetWare[®] Accelerated Upgrade utility is an advanced utility that can be used to upgrade a NetWare 4.11, NetWare 4.2, or NetWare 5 server to NetWare 6. NetWare Accelerated Upgrade is intended for use by network administrators who are skilled at troubleshooting and installing NetWare networks.

WARNING: Back up all data before using this utility. Although NetWare Accelerated Upgrade can reduce the time required to upgrade multiple servers, it must be used carefully. There are no backout procedures that will restore your servers to their original configuration or restore trustee assignments if the upgrade is unsuccessful.


Two advantages to using NetWare Accelerated Upgrade are that:

- ♦ It runs on a Windows client workstation, so you don't need to be physically present at the server console. You also have the option of customizing the NetWare Accelerated Upgrade script files, which allows you the flexibility of customizing the NetWare 6 installation.
- ♦ It is quicker than the standard installation process; however, it does not install additional network products or licensing certificates.

How NetWare Accelerated Upgrade Works

NetWare Accelerated Upgrade requires a Windows client workstation, a staging server, and a NetWare 4 or 5 server targeted for upgrade.

The staging server holds a copy of the *NetWare 6 Operating System* CD files. From this one location, all targeted servers can be upgraded.



After the *NetWare 6 Operating System* CD files are copied to the staging server, you will log in to a Windows workstation and launch the NetWare Accelerated Upgrade utility (ACCUPG.EXE), located at the root of the *NetWare 6 Operating System* CD. When NetWare Accelerated Upgrade launches, you will log in to the target and staging servers.

During the upgrade, NetWare Accelerated Upgrade compares the existing target server properties, such as the Directory Services version and the CLIB version, with the minimum upgrade requirements for those properties.

If you meet the minimum requirements, NetWare Accelerated Upgrade copies the NetWare 6 CD files from the staging server to the target server. After the file copy, the target server reboots to complete the NetWare 6 server upgrade.

Before you begin upgrading the server, make sure that you have the following software:

- ♦ *NetWare 6 Operating System* CD
- ♦ *NetWare 6 License/Cryptography* diskette for each server plus five connections if you do not have an MLA

Upgrading to NetWare 6

To run NetWare Accelerated Upgrade, complete the following tasks:

1. [Prepare the Workstation \(page 13\)](#)
2. [Prepare a Staging Server \(page 13\)](#)
3. [Prepare the Network \(page 17\)](#)
4. [Prepare the Target Server \(page 15\)](#)
5. [Run NetWare Accelerated Upgrade \(page 18\)](#)
6. [Complete Post-Upgrade Tasks \(page 20\)](#)

Prepare the Workstation

- ☐ A Windows 95/98, Windows NT*, Windows 2000, or Windows ME workstation with 50 MB of available disk space.
 - ♦ The Windows 95/98 and Windows ME workstations must be running Novell® Client™ version 3.3 or later and Support Pack 1 or later
 - ♦ The Windows NT and Windows 2000 workstations must be running Novell Client for Windows version 4.8 or later and Support Pack 1 or later
- ☐ PS/2* or serial mouse recommended, but not required.

Continue with the next section, "[Prepare a Staging Server](#)."

Prepare a Staging Server

The staging server holds a copy of the *NetWare 6 Operating System* CD files. From this one location, all targeted servers can be upgraded. The staging server can be any server other than the server you plan to upgrade and the client workstation you are using to run NetWare Accelerated Upgrade.

- 1 Do one of the following:
 - ♦ Copy the *NetWare 6 Operating System* CD files to a volume on the staging server. Make sure that all target servers can access the staging server and the client workstation.
 - ♦ Mount the *NetWare 6 Operating System* CD as a volume on the staging server.

2 (Conditional) If you are upgrading a target server that does not have NCI installed, copy the NetWare 6 NCI file to your target server. Do one of the following:

- ♦ If you copied the NetWare 6 CD files in **Step 1 on page 13**, create directory named License at the root of the copied *NetWare 6 Operating System* CD and then copy the #.NFK file from the *NetWare 6 License/Cryptography* diskette to the newly created License directory.
- ♦ If you mounted the *NetWare 6 Operating System* CD, rename the #.NFK file to NICIFK (no extension is needed) and then copy the #.NFK to the SYS:SYSTEM directory on *every* target server that you plan to upgrade that does not have the NCI installed.

3 (Optional) Specify disk drivers manually.

Although not recommended, you can load disk drivers that are not provided on the *NetWare 6 Operating System* CD or bypass the hardware auto-detection used while running NetWare Accelerated Upgrade. For more information, see “**Specifying Disk Drivers Manually**” on page 20.

4 (Optional) Customize the NetWare Accelerated Upgrade script files.

WARNING: Customizing the installation process could affect the way that NetWare 6 is installed. This might result in an upgrade failure and might make your server unusable.

Customizing script files lets you add more menu options or install additional software or patches that are not standard features of the NetWare 6 installation.

For information on using script files, see "Upgrading an Enterprise Using the NetWare Accelerated Upgrade" (*AppNotes*, April 1999) at the [Novell Developer Net Web site \(http://developer.novell.com/research/completearchive.htm\)](http://developer.novell.com/research/completearchive.htm).

When the source server is ready, continue with the next section, "**Prepare the Target Server.**"

Prepare the Target Server

The target server is the NetWare 4 or NetWare 5 server that you plan to upgrade to NetWare 6. Make sure your target server meets the *minimum* requirements listed below.

WARNING: Do not use NetWare Accelerated Upgrade to upgrade the first server in your tree to NetWare 6. You must already have a server running NetWare 6 in your tree in order to use NetWare Accelerated Upgrade. If you do not already have a server running NetWare 6, do an inplace upgrade on a server in your tree, and then upgrade the rest of the servers in your tree with NetWare Accelerated Upgrade.

- ☐ A server-class PC with Pentium* Pro or Pentium II or higher processor with a minimum of 180 MB of RAM. 512 MG of RAM is recommended.

HINT: 180 MB is the minimum requirement. If you plan to install additional products after the upgrade, you might want to take into account the additional memory requirements those products will have and plan for them now.

- ☐ Make sure the target server has enough disk space.
 - ◆ 30 MB of available disk space on the DOS partition. The recommended total size of the DOS partition is 100 MB.
 - ◆ 1 GB minimum *available* disk space on volume SYS:. However, the total recommended size of volume SYS: is 2 GB.
- ☐ (Optional) Load the RSPX and REMOTE NLM™ programs (for the IPX™ protocol) or the RCONJAG6.NLM program (for the IP protocol) on the target server if you are using script files to upgrade your server and you want to see and access the target server's server console from the client workstation.
- ☐ (Conditional) If your target server is running ZENworks™ for Servers 2, you must unload this application before upgrading your server. For more information about upgrading servers with ZENworks, see [ZENworks for Server 2 Installation and Setup Guide \(http://www.novell.com/documentation/lg/zfs2/index.html\)](http://www.novell.com/documentation/lg/zfs2/index.html) > Installing and Setting Up Management and Monitoring Services > Setting Up Management and Monitoring > Starting and Stopping Services.

To stop the Policy and Distribution Services, follow these steps:

- ◆ Enter **CTRL/ESC** at the server console of the NetWare server to list the processes that are currently running.
- ◆ Select Distributor from the list.

- ◆ Prompt enter **Exit**, at the Distributor console.
- ◆ Select Subscriber from the list.
- ◆ Prompt enter **Exit**, at the Subscriber console.
- ◆ Select ZENworks for Servers from the list.
- ◆ Prompt enter **Exit**, at the ZENworks for Servers console.
- ◆ Select Remote Web Console from the list.
- ◆ Prompt enter **Exit**, at the Remote Web Console.

The following table lists the procedures that NetWare Accelerated Upgrade does not support during a NetWare 4 or NetWare 5 upgrade.

Table 1 Unsupported Procedures When Upgrading a NetWare 4 or NetWare 5 Target Server

Not Supported during an Upgrade	Recommendation
Adding the IP protocol during the upgrade	Add the IP protocol after upgrading by using NetWare 6 utilities such as INETCFG, or use the NetWare 6 Installation program to upgrade.

Once you have met the hardware requirements, complete the following steps to prepare your target server to be upgraded:

- 1** Update the target server with the latest NetWare Support Pack.

Support Packs are available at the [Novell Support Web site \(http://www.support.novell.com/filefinder\)](http://www.support.novell.com/filefinder).

- ◆ NetWare 4.11 and NetWare 4.2 require NetWare 4 Support Pack 8 (IWSP6A.EXE) or later
- ◆ NetWare 5.0 requires NetWare 5 Support Pack 6 or later
- ◆ NetWare 5.1 requires NetWare 5 Support Pack 2 or later

- 2** (Conditional) If you are upgrading a server in a multiserver tree that is running NDS[®] 7 with NSS volumes, do the following:

2a Run the NetWare Deployment Manager utility (NWDEPLOY.EXE), located at the root of the *NetWare 6 Operating System* CD.

2b Click Network Preparation > Prepare a Server with NDS 7 & NSS.

- 3** (Conditional) If you are upgrading a server in a multiserver tree that is clustered, do the following:
 - 3a** Run the NetWare Deployment Manager utility (NWDEPLOY.EXE), located at the root of the *NetWare 6 Operating System* CD.
 - 3b** Click Network Preparation > Prepare a Novell Cluster for Upgrade.
- 4** Run DSREPAIR > Time Synchronization at the server console of the target server. If you encounter any NDS[®] synchronization errors, make sure you resolve these before continuing.
- 5** Mount all volumes.

If you have experienced disk errors in the past, you might want to run VREPAIR on all of the volumes on the server to ensure that there are no errors.
- 6** Verify that your target server can communicate with your staging server and your client workstation.

IMPORTANT: Make sure that the client workstation, target server, and staging server share the same protocol (IPX™ or IP).

If you have problems here, refer to “[Troubleshooting Server-to-Server Connections](#)” on page 21.
- 7** Make sure that you have the Supervisor right to the container where the target server resides.

When the target server is ready, continue with the next section, “[Prepare the Network](#).”

Prepare the Network

Because you cannot use NetWare Accelerated Upgrade to upgrade the first server in a multiserver tree to NetWare 6, you must do an inplace upgrade on one server in your tree. Once there is a server in your tree running NetWare 6, you can safely upgrade the rest of your servers using NetWare Accelerated Upgrade.

For instructions on performing an inplace upgrade, refer to Chapter 3, “[Upgrade to NetWare 6](#)” in the *NetWare 6 Overview and Installation Guide*.

If you are upgrading a server in a single-server tree to NetWare 6, you can use NetWare Accelerated Upgrade; however, you will need to manually extend the NDS schema after the upgrade. If you want the schema updated automatically, it is best to do an inplace upgrade.

Continue with the next section, “[Run NetWare Accelerated Upgrade](#).”

Run NetWare Accelerated Upgrade

- 1** From your workstation, log in to the staging server and double-click the NetWare Accelerated Upgrade executable (ACCUPG.EXE), located at the root of the *NetWare 6 Operating System* CD.
- 2** Read the Welcome screen and click the right-arrow.
- 3** Enter the location where you copied or mounted the NetWare 6 files to the staging server and click the right-arrow.
- 4** Enter the password to the staging server (the server that holds the copy of the NetWare 6 CD files) and click OK.
- 5** Select your target server from the list and click the right-arrow.
- 6** If prompted, enter the username, password, tree name and context for the target server, and then click OK.
- 7** Click the right-arrow.

At this point, NetWare Accelerated Upgrade checks the target server to make sure that the selected server meets the minimum software and hardware requirements of NetWare 6. This might take a few minutes.

- 8** Review the critical requirement screen and make sure that the target server meets the minimum NetWare 6 server requirements.

NOTE: If you have applied the Support Packs listed in the “[Prepare the Target Server](#)” on [page 15](#), you won’t have any problems meeting these requirements.

Some items appearing on the list are not critical requirements. But the following requirements *must* be met before continuing:

- ♦ NetWare server version
- ♦ Directory Services version
- ♦ CLIB version
- ♦ HCSS is *not* loaded (NetWare 4 only)
- ♦ SFT™ III™ server is *not* used (NetWare 4 only)
- ♦ Unsupported drivers are unloaded (NetWare 4 only)

If the target server does not meet a *critical* minimum requirement, the server property will be listed in red. NetWare Accelerated Upgrade will not allow you to continue until you have met all *critical* minimum requirements.

IMPORTANT: If prompted to update your NICI file, follow the instructions in [Step 2 on page 14](#) before continuing.

- 9** Check any of the following options that you want NetWare Accelerated Upgrade to automatically perform during the upgrade, and then click the right-arrow:

- ♦ Reboot the target server after the upgrade is completed.

Even if you checked this option, there might be an instance where you might need to manually reboot the target server once the file copy is complete.

- ♦ Update the existing drivers on the target server to NetWare 6 LAN and disk drivers.

Because NetWare Accelerated Upgrade has renamed the STARTUP.NCF file to STARTUP.AUP, during auto-detection, NetWare Accelerated Upgrade will restore the original STARTUP.NCF and then loads the appropriate .HAM and .CDM drivers that NetWare 6 supports.

If device drivers are not found for a device currently loaded in the former STARTUP.NCF or AUTOEXEC.NCF files, the LOAD line will be deleted or copied to the new file and then commented out.

WARNING: If the target server contains any disk drivers that are not compatible with NetWare 6, they cannot be replaced during the hardware auto-detection process and your server cannot be upgraded. To avoid this, unload any drivers that are not compatible with NetWare 6 before you complete the upgrade. NetWare Accelerated Upgrade automatically detects unsupported drivers and will warn you about proceeding.

- ♦ Remove any unsupported DOS utilities existing on the target server (NetWare 4 servers only).

- 10** Review the list of products that NetWare Accelerated Upgrade is going to install and click the right-arrow.

Once you click the right-arrow, you might need to wait a few minutes before the Progress Screen appears.

- 11** Monitor the Progress Screen and click Close when the NetWare 6 Operating System files have been copied to the target server.

Your target server has now been upgraded to a NetWare 6 server. NetWare Accelerated Upgrade does not install additional network products during the upgrade. To install additional network products, see [“Installing Additional Networking Products” on page 20](#).

Continue with [“Complete Post-Upgrade Tasks.”](#)

Complete Post-Upgrade Tasks

Installing Licensing Certificates

Because the NetWare Accelerated Upgrade utility does not install licenses, use iManage via NetWare Web Manager to install license certificates on the new NetWare 6 server.

NOTE: If licenses are installed at the [Root] of the NDS tree or you are on an MLA account, you might not need to install additional licenses.

- 1 Go to NetWare Web Manager by entering the following into a Web browser:

`https://nw6serveripaddress:portnumber`

- 2 Click the iManage icon.
- 3 Click License Management > Install Licenses.
- 4 Follow the on-screen instructions.

Installing Additional Networking Products

NetWare Accelerated Upgrade does not install additional products. If you want to add network products, you can do so in one of two ways:

- ♦ Through the server console by clicking the Novell icon on the servertop and then Install.
- ♦ Through Deployment Manager (located at the root of the *NetWare 6 Operating System* CD).

Specifying Disk Drivers Manually

You might want to change the behavior of hardware detection and the NDS database upgrade. By replacing the -U option with the -MU option from the lines that load HDETECT.NLM in the HWDETECT.ICS script file, you can confirm or add new hardware devices during the upgrade.

To confirm or add new hardware devices during the upgrade, you must physically be at the server console of the target server.

This procedure can also be used to load disk drivers that are not provided on the *NetWare 6 Operating System* CD. This action might be beneficial when upgrading multiple servers with identical hardware components. If you select

specific drivers manually, you must create and configure a \STARTUP directory that contains the disk drivers and the STARTUP.NCF file.

- 1 Copy the *NetWare 6 Operating System* CD files to a volume on a staging server.

IMPORTANT: Do not copy the files onto the target server that you are upgrading or onto the client workstation.

- 2 Make sure that the target server can connect to the staging server.
- 3 Copy any additional .HAM and .CDM disk drivers that you need to the \STARTUP directory on the staging server.
- 4 Continue with “Prepare the Network” on page 17.

Troubleshooting Server-to-Server Connections

If you could not make a server-to-server connection during NetWare Accelerated Upgrade, try one or more of the possible solutions.

Disabling SAP Filtering

- 1 At the server console of the target server, enter
INETCFG
- 2 Select Protocols > IPX > Filtering Support.

If SAP filtering cannot be disabled, make sure that the client workstation is on the same LAN segment as the target and staging servers.

Detaching from Unauthenticated Servers

- 1 From a Windows 95/98 or Windows NT client, right-click the red Novell N.
- 2 Click NetWare Connections.
- 3 Select the server that you are not authenticated to.
- 4 Click Detach.

If you are still having problems communicating with the target server, reboot the client workstation and try to log in to the target server again.

Setting the Target Server's Gate Parameter to Its Default Router IP Address

For a NetWare 4 Target Server

- 1 At the server console, enter

LOAD INSTALL

- 2 Select NCF Files Options > Edit AUTOEXEC.NCF File.

- 3 In the AUTOEXEC.NCF file, add

LOAD TCP/IP

- 4 Add a command that loads the network board and specifies the slot, frame, and name of the network board (the AUTOEXEC.NCF file should list this information).

For example, if you had a NE2000™ network board located in slot 3 with an Ethernet_II frame, you would add a command similar to the following:

LOAD NE2000 Slot=3 Frame=ethernet_II Name=NE2000

- 5 Add a command that will load the network board and its IP address, mask address, and gate parameter (set this to the default router IP address of the target server).

For example, for the NE2000 network board with a default router IP address of 137.33.172.1, the command would be similar to the following:

**LOAD NE2000 addr=137.65.178.1 mask=255.255.255.0
gate=137.33.172.1**

- 6 Add a command to bind IP to the network board, using the following format:

BIND IP *network_board_name*

- 7 Next, add the IP address, mask address, and gate parameter for the target server to the BIND IP command line.

For a NetWare 5 Target Server

- 1 At the server console, enter

NWCONFIG

- 2 Select NCF Files Options > Edit AUTOEXEC.NCF File.

- 3** At the BIND IP command line, after the mask address, set the gate parameter to the default router IP address for the target server.

For example, if your default router IP address was 137.65.178.1, at the BIND IP command line you would enter the following after the mask address:

gate=137.65.178.1

2

Automating the NetWare Installation with a Response File

Installing the NetWare[®] operating system software can be easier and more flexible when you use a response file. When used with the graphical server installation, a response file lets you

- ♦ Set and display specific defaults
- ♦ Bypass entire sections of the installation
- ♦ Automate the entire server installation process

A response file is a text file containing sections and keys (similar to a Windows .INI file). You can create a response file using any ASCII editor.

If you use a response file, the NetWare server installation reads the installation parameters directly from the response file, replacing the default installation values with response file values. The installation program accepts the values as they appear and continues to the next installation screen. Because the installation program gets all the required information from the response file, you can even skip the entire sequence of installation screens.

Using a response file to install NetWare can be very useful to a variety of customers and vendors. Novell[®] customers who have established server hardware standards in their enterprise can use the response file to rapidly deploy multiple NetWare servers. They will also find the response file useful for preconfiguring some of the NetWare installation, while leaving other parameters to the local administrator. Resellers and OEMs will find the response file useful for pre-installing NetWare prior to shipping a server to their customers.

This chapter contains the following sections:

- ♦ “Creating a Response File” on page 26
- ♦ “Using a Response File” on page 27
- ♦ “Syntax” on page 28
- ♦ “NetWare Sections and Keys” on page 33
- ♦ “Performing a Fully Automated Installation” on page 78
- ♦ “Automating the Installation of Additional Products and Services” on page 79
- ♦ “CD Boot and the Response File” on page 87
- ♦ “Customizing the Installation Using Install Scripts” on page 87
- ♦ “Performing a Factory Install” on page 90

Creating a Response File

You can create a new response file, or edit one from a previous server installation.

NOTE: You should take care when using a response file from a previous installation because it can contain advanced configuration options you don’t want for your current installation.

Creating a New Response File

- 1 Open an ASCII editor such as EDIT.
- 2 Input parameters as described in “Syntax” on page 28.

Editing a Response File from a Previous Server Installation

You can generate a response file from a server installation or upgrade, and then use it as input for additional server installations or upgrades. Using the response file from another server installation works best when both servers have the same hardware configurations.

- 1 Perform the first server installation, and then reboot the server by clicking Yes on the closing screen of the installation.
- 2 Log in to the new server after it has been rebooted.

- 3 Copy RESPONSE.NI from the SYS:NI\DATA directory to either a diskette or to the new server.
- 4 Modify the file by adjusting the parameters and removing unwanted sections.

See “Syntax” on page 28 for a description of the parameters

Using a Response File

A response file can be used during a server installation in one of two ways:

- ♦ Identified during the server installation
- ♦ Entered at the command line

Using a Response File during a Server Installation

- 1 Copy the response file to a diskette, hard disk, or network directory accessible by the PC that you are installing NetWare on.
- 2 Enter **INSTALL** to start the server installation.
- 3 On the Install Options screen (the first screen after the language section), press F3 for the response file window.
- 4 Enter the path for the response file, and then press Enter.
- 5 Continue with the rest of the server installation.

Entering a Response File at the Command Line

- 1 Copy the response file to a diskette, hard disk, or network directory accessible by the server that you are installing NetWare on.
- 2 Start the server installation from CD, hard disk, or network directory by entering

INSTALL /RF=*response_file_DOS_path\filename*

Replace *response file DOS path* with the path for the response file, and *filename* with the name of the response file. For example, if you are installing NetWare from a CD and the response file is on a diskette, enter

D:\INSTALL /RF=A:\RESPONSE.TXT

Syntax

A response file is a Windows .INI-type file. Data items are identified as keys, and keys have associated values (Key = value). These keys are grouped in sections. For the NetWare installation program, each data input screen has one or more sections associated with it. Section names of the installation generally correspond to the function of the screens.

Section and key names are case sensitive. Values associated with keys are not case sensitive. Semicolons placed at the beginning of a line indicate that the line is a comment.

Sections can be placed in any order. However, if there are two or more sections with the same section name, the first section listed in the response file will be used and the other sections will be ignored.

The following sections apply to the NetWare server installation. They are listed in the order they are used during installation.

Section	Purpose
"[NWI:Product Information] Section" on page 33	Identifies the specific product version the response file is associated with.
"[NWI:Language] Section" on page 34	Specifies the languages to be installed on the server.
"[NWI:Install Options] Section" on page 35	Corresponds to the first data input screen.
"[NWI:Server Settings] Section" on page 37	Corresponds to the server settings screen.
"[NWI:Locale] Section" on page 38	Corresponds to the regional settings screen.
"[NWI:Mouse and Video] Section" on page 39	Corresponds to the video and mouse settings screen.
"[NWI:Hardware] Section" on page 40	Corresponds to the hardware detection and driver matching function of the installation program. If drivers are found in the Update directories, they will be used instead of the drivers found on the NetWare CD.

Section	Purpose
“[NWI:Excluded From Detection] Section” on page 44	Identifies what drivers will be excluded from the auto-detection.
“[NWI:Multi-Processor System] Section” on page 44	Identifies the driver associated with the processor system in the server.
“[NWI:Storage Adapter n] Section” on page 45	Identifies the driver and its associated parameters for a specific storage adapter. This Section can be duplicated for as many adapters as are in the server. <i>n</i> uniquely identifies the sequence of the Section (for example, 1, 2, etc.).
“[NWI:Storage Device n] Section” on page 46	Specifies storage devices. This section can be duplicated for as many devices as are in the server. <i>n</i> uniquely identifies the sequence of the Section (for example, 1, 2, etc.).
“[NWI:Network Adapter n] Section” on page 47	Identifies the driver and its associated parameters for a specific network adapter. This section can be duplicated for as many devices as are in the server. <i>n</i> uniquely identifies the sequence of the Section (for example, 1, 2, etc.).
“[NWI:Reserved Adapter n] Section” on page 50	Specifies the adapters that are to be reserved.
“[NWI:Hotplug System] Section” on page 50	Identifies the driver associated with the processor system in the server.
“[NWI:NetWare Loadable Module] Section” on page 51	Identifies NLM™ programs that are to be loaded with the hardware drivers.
“[NWI:Misc] Section” on page 59	Functions as a container of parameters that do not correspond to a data input screen.
“[NWI:File System] Section” on page 51	Specifies the parameters for the partitions and volumes.
“[NWI:File Server] Section” on page 60	Specifies the parameters that uniquely identify the server.

Section	Purpose
"[NWl:Protocols] Section" on page 61	Controls whether the protocol screen is displayed.
"[NWl:TCPIP] Section" on page 62	Specifies TCP/IP parameters.
"[NWl:IPX] Section" on page 63	Specifies IPX™ parameters.
"[NWl:IPCMD] Section" on page 64	Specifies Compatibility Mode parameters.
"[NWl:SNMP] Section" on page 65	Specifies Simple Network Management Protocol parameters.
"[NWl:DNS] Section" on page 67	Specifies Domain Name Service (DNS) parameters.
"[NWl:Host Name] Section" on page 68	Specifies DNS Host Name for each IP address.
"[NWl:Time Zone] Section" on page 69	Corresponds to the time zone screen.
"[NWl:Time Synchronization] Section" on page 70	Specifies time server configuration.
"[NWl:NDS] Section" on page 70	Corresponds to the NDS® screen.
"[NWl:License] Section" on page 74	Identifies the location of the license file.
"[NWl:Add to Startup] Section" on page 76	Specifies lines to be added to the STARTUP.NCF file.
"[NWl:Append To Autoexec.ncf] Section" on page 77	Specifies lines to be added to the AUTOEXEC.NCF file.
"[NWl:Use NCF Settings] Section" on page 77	Specifies whether to use the response file or the AUTOEXEC.NCF file for the server name during an upgrade.
"[Novell:NOVELL_ROOT:1.0.0] Section" on page 78	Specifies full automation of installation.
"[Selected Nodes] Section" on page 80	Specifies full automation of products and services.
"[LDAP] Section" on page 83	Specifies full automation of products and services.

Section	Purpose
"[Novell:DNS_DHCP:1.0.0] Section" on page 85	Specifies full automation of products and services.
"[NWl:Install Script] Section" on page 88	Specifies full automation of products and services.
"[NWl:Factory] Section" on page 91	Specifies full automation of factory install.
"[Novell:StartupDirectory:1.0.0] Section" on page 92	Specifies full automation of factory install.
"[Novell:SYSDirectory:1.0.0] Section" on page 92	Specifies full automation of factory install.
"[Novell:ConfigDirectory:1.0.0] Section" on page 93	Specifies full automation of factory install.
"[Novell:LANFiles:1.0.0] Section" on page 93	Specifies full automation of factory install.
"[Novell:SBDFiles:1.0.0] Section" on page 94	Specifies full automation of factory install.
"[Novell:portalzip:1.0.0] Section" on page 94	Specifies full automation of factory install.
"[Novell:Rconjzip:1.0.0] Section" on page 95	Specifies full automation of factory install.
"[Novell:Perl5zip:1.0.0] Section" on page 95	Specifies full automation of factory install.
"[Novell:beanszip:1.0.0] Section" on page 96	Specifies full automation of factory install.
"[Novell:scripteszip:1.0.0] Section" on page 97	Specifies full automation of factory install.
"[Novell:scripteszip:1.0.0] Section" on page 97	Specifies full automation of factory install.
"[Novell:console1zip:1.0.0] Section" on page 97	Specifies full automation of factory install.
"[Novell:ldapzip:1.0.0] Section" on page 98	Specifies full automation of factory install.
"[Novell:wanmanzip:1.0.0] Section" on page 98	Specifies full automation of factory install.

The Prompt key is listed with each section that corresponds to a data input screen and it

- ♦ Controls whether the screen will be displayed.
- ♦ Lets you use the response file to pass in the keys and values of the section.
- ♦ Lets you bypass the screen.

If the value of Prompt is True, the screen will be displayed and the data specified in the response file will be presented as default values. The screen will not be displayed if the value of Prompt is False. If any of the required data is missing in the response file, however, the screen will be shown regardless of the Prompt value. For more information on each section's keys, see [“NetWare Sections and Keys” on page 33](#).

In the following example, the data input screen will be displayed with the NDS information already filled in:

```
[NWI:NDS]
Prompt = True
Tree Name = Novell
New Tree = True
Server Context = 0=Utah
Admin Context = 0=Utah
Admin Login Name = Admin
Admin Password = install
Display Summary = True
```

In the following example, the NDS input screen and the Summary screens will not be displayed and the NetWare installation program will bypass them.

```
[NWI:NDS]
Prompt = False
Tree Name = Novell
New Tree = True
Server Context = 0=Utah
Admin Context = 0=Utah
Admin Login Name = Admin
Admin Password = install
Display Summary = False
```

NetWare Sections and Keys

The NetWare installation sections and their associated keys are specified below. Section names and Key names are in bold. Included with each key are the default value, possible values, whether the Key is required for the NetWare installation to run silently (for example, to create a new NDS tree without any user input, New Tree=True must appear in the response file). Also included with each Key is a short description of the Key's purpose.

[NWI:Product Information] Section

Major Version = <string>

Default	NetWare 6
Values	(product name)
Key Required	Yes
Example	Major Version = NetWare 6
Purpose	Specifies the name of the product that this response file is associated with. If this value does not match that of the NetWare default response file (normally found in the INSTALL directory on the CD), the installation will not continue.

Minor Version = <integer>

Default	10
Value	0-99
Key Required	Yes
Example	Minor Version = 10
Purpose	Specifies the revision level of the product. If this value does not match that of the NetWare default response file (normally found in the INSTALL directory on the CD image), the installation will not continue.
	NOTE: The default value was inadvertently left at 0 for the English version release. The error was corrected in the international release.

Small Business = <string>

Default	False
Value	True or False
Key Required	No
Example	Small Business = True
Purpose	Controls whether the Small Business licensing model is used.

[NWI:Language] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the screen is displayed.

Server Language = <integer>

Default	4 (English)
Values	1-100
Key Required	Yes
Example	Server Language = 4
Purpose	Specifies the language that the screens of the installation program will be displayed in and that will be the default language of the server.

Additional Languages = <integers separated by commas>

Default	(none)
Values	1-100 (values are specified in INSTALL\PROFILE.TXT)
Key Required	No
Example	Additional Languages = 5,6
Purpose	Specifies additional languages that will be installed on the server.

[NWI:Install Options] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the screen is displayed.

Upgrade = <string>

Default	False
Values	True or False
Key Required	Yes
Example	Upgrade = False
Purpose	Specifies whether the installation will be an upgrade or a new installation. False specifies a new installation rather than an upgrade.

Startup Directory = <string>

Default	C:\NWSERVER
Values	(existing DOS path up to 255 characters)
Key Required	Yes
Example	Startup Directory = C:\NWSERVER
Purpose	Identifies the directory where the server's initialization files will reside on the Boot Partition.

Allow User response file = <string>

Default	True
Values	True or False
Key Required	No
Example	Allow User response file = True
Purpose	Makes the F3 key available on the opening screen. It allows a user to input a path to an additional response file. NOTE: Values in a user response file will override the values of other response files passed in previously to the installation program.

Abort on Error = <string>

Default	False
Values	True or False
Key Required	No
Example	Abort on Error = True
Purpose	Specifies whether the installation will halt when an error is encountered during an unattended installation. The user will normally see an error screen if this key is set to False.

[NWI:Server Settings] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the screen is displayed.

NDS Version = <integer>

Default	8
Values	7 or 8
Key Required	Yes
Example	NDS Version = 8
Purpose	Specifies the version of NDS to install on this server.

Load Server at Reboot = <string>

Default	True
Values	True or False
Key Required	No
Example	Load Server at Reboot = True
Purpose	Adds new AUTOEXEC.BAT and CONFIG.SYS files that sets a minimal DOS environment and automatically loads the server. Pre-existing AUTOEXEC.BAT and CONFIG.SYS files on the server will be renamed to *.000. If this value is set to True and AUTOEXEC.000 already exists, then AUTOEXEC.BAT will be renamed to AUTOEXEC.001, etc.

CD Driver = <string>

Default	NetWare
Values	NetWare or DOS
Key Required	No
Example	Source Media Access = NetWare
Purpose	Determines the driver type (DOS or server) used to access the CD during installation.

[NWI:Locale] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the screen is displayed.

Country Code = <integer>

Default	001
Values	(Values are specified in <i>INSTALL\NLS\language number\LOCALE.TXT</i>)
Key Required	Yes
Example	Country Code = 001
Purpose	Specifies the country-oriented settings for display.

Code Page = <integer>

Default	437
Values	(values are specified in INSTALL\NLS\language number\LOCALE.TXT)
Key Required	Yes
Example	Code Page = 437
Purpose	Sets the character set for the server.

Keyboard = <string>

Default	United States
Values	(values are specified in INSTALL\NLS\<language number>\LOCALE.TXT)
Key Required	Yes
Example	Keyboard = United States
Purpose	Sets the keyboard type.

[NWI:Mouse and Video] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the screen is displayed.

Mouse = <string>

Default	PS/2
Values	PS/2, Serial COM1, Serial COM2, No Mouse (values are specified in INSTALL\NLS\language number\LOCALE.TXT)
Key Required	Yes
Example	Mouse = PS/2
Purpose	Specifies the mouse type that will be used for the graphical portion of the installation.

Use Super VGA = <string>

Default	True
Values	True or False
Key Required	No
Example	Use Super VGA = True
Purpose	Indicates whether 256-color Super VGA is set for the graphical portion of the installation. If set to False, 16-color Standard VGA is set.

[NWI:Hardware] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the screen is displayed.

Update Storage Driver Directory = <DOS path>

Default	(none) The Install always looks in C:\NWUPDATE as well.
Values	(existing DOS path up to 255 characters)
Key Required	No
Example	Update Storage Driver Directory = F:\DRV\UPDATE
Purpose	Specifies the directory path where updated storage (HAM and CDM) drivers will be found; the directory should already exist and be a local DOS path. NOTE: Associated DDI files must accompany the storage drivers in this directory.

Update Network Driver Directory = <DOS path>

Default	(none) The Install always looks in C:\NWUPDATE as well.
Values	(existing DOS path up to 255 characters)
Key Required	No
Example	Update Network Driver Directory = F:\DRV\UPDATE
Purpose	Specifies the directory path where updated network (LAN) drivers will be found; the directory should already exist and be a local DOS path. NOTE: Associated LDI files must accompany the storage drivers in this directory.

Update PSM Driver Directory = <DOS path>

Default	(none) The Install always looks in C:\INWUPDATE as well
Values	(existing DOS path up to 255 characters)
Key Required	No
Example	Update PSM Driver Directory = F:\DRV\UPDATE
Purpose	Specifies the directory path where updated processor (PSM) drivers will be found; the directory should already exist and be a local DOS path. NOTE: Associated PDI files must accompany the storage drivers in this directory.

Update Source Drive Type = <string>

Default	(the type of the install source)
Values	Floppy or CD or Network or Other
Key Required	No, unless one or more of the Update keys above are set.
Example	Update Source Drive Type = Network
Purpose	Specifies the type of all source directories identified in the keys above; all directories must be of the same type.

PSM Detection = <string>

Default	True
Values	True or False
Key Required	No
Example	PSM Detection = True
Purpose	Controls whether driver matching is performed for the processor system. If driver information is identified in the response file (see Multi-Processor System section), detection can be set to False.

Storage Detection = <string>

Default	True
Values	True or False
Key Required	No
Example	Storage Detection = True
Purpose	Controls whether detection of storage adapters and driver matching is performed. If storage adapter and driver information is identified in the response file (see Storage Adapter section), detection can be set to False.

Network Detection = <string>

Default	True
Values	True or False
Key Required	No
Example	Network Detection = True
Purpose	Controls whether detection of network adapters and driver matching is performed. If network adapter and driver information is identified in the response file (see Network Adapter section), detection can be set to False.

Device Detection = <string>

Default	True
Values	True or False
Key Required	No
Example	Device Detection = True
Purpose	Controls whether detection of storage devices and driver matching is performed. If storage adapter and driver information is identified in the response file (see Storage Device section), detection can be set to False.

HotPlug Detection = <string>

Default	True
Values	True or False
Key Required	No
Example	HotPlug Detection = True
Purpose	Controls whether detection of Hot Plug devices and driver matching is performed.

[NWI:Excluded From Detection] Section

Driver File = <filename>

Default	(none)
Values	(name of driver)
Key Required	No
Example	Driver File =AHA2940.HAM
Purpose	Identifies the driver that will be excluded from auto-detection.

[NWI:Multi-Processor System] Section

Driver File = <filename>

Default	(none)
Values	(name of driver)
Key Required	No, unless PSM Detection=False
Example	Driver File = MPS14.PSM
Purpose	Identifies the driver to use for the server's multiprocessor system.

[NWI:Storage Adapter *n*] Section

Example	[NWI:Storage Adapter 1]
Description	This section can be included for each storage adapter in the server. Several Keys are described under this section which are optional; if the driver is detectable by NetWare, only the Driver File key is required for the section. The other Keys and Values are varied and are extracted from the driver's corresponding DDI file.

Driver File = <filename>

Default	(none)
Values	(name of driver)
Key Required	No, unless Storage Detection=False
Example	Driver File = AHA2940.HAM
Purpose	Identifies the driver to use for the storage adapter.

SLOT = <integer>

Default	(none)
Values	(can be a 5-digit Hardware Instance Number assigned on servers with buses that support detection—such as PCI)
Key Required	No, unless the driver is for an ISA adapter
Example	SLOT = 2
Purpose	Specifies the bus slot of the storage adapter to which the driver should be loaded.

INT = <hexadecimal number>

Default	(none)
Values	1-F
Key Required	No, unless the driver is for an ISA adapter.
Example	INT = F
Purpose	Specifies the interrupt that the adapter is set to; this parameter is commonly used for ISA bus adapters.

PORT = <number>

Default	(none)
Values	(3-digit memory address)
Key Required	No, unless the driver is for an ISA adapter
Example	PORT = 170
Purpose	Specifies the memory address the adapter is set to; this parameter is commonly used for ISA bus adapters.

[NWI:Storage Device *n*] Section

Example	[NWI:Storage Device 1]
Description	This section can be included for each storage device in the server.

Driver File = <filename>

Default	(none)
Values	(name of driver)
Key Required	No, unless Device Detection=False
Example	Driver File = IDECD.CDM
Purpose	Identifies the driver to use for the storage device.

[NWI:Network Adapter *n*] Section

Example	[NWI:Network Adapter 1]
Description	This section can be included for each network adapter in the server. Several Keys are described under this section which are optional; if the driver is detectable by NetWare, only the Driver File Key is required for the section. The other Keys and Values are varied and are extracted from the driver's corresponding LDI file.

Driver File = <filename>

Default	(none)
Values	(name of driver)
Key Required	No, unless Network Detection=False
Example	Driver File = 3C59X.LAN
Purpose	Identifies the driver to use for the network adapter.

SLOT = <integer>

Default	(none)
Values	(can be a 5-digit Hardware Instance Number assigned on servers with buses that support detection—such as PCI)
Key Required	No, unless the driver is for an ISA adapter
Example	SLOT = 10001
Purpose	Specifies the bus slot of the network adapter to which the driver should be loaded.

INT = <hexadecimal number>

Default	(none)
Values	1-F
Key Required	No, unless the driver is for an ISA adapter
Example	INT = F
Purpose	Specifies the interrupt that the adapter is set to; this parameter is commonly used for ISA bus adapters.

PORT = <number>

Default	(none)
Values	(3-digit memory address)
Key Required	No, unless the driver is for an ISA adapter
Example	PORT = 170
Purpose	Specifies the memory address the adapter is set to; this parameter is commonly used for ISA bus adapters.

Adapter Name = <string>

Default	(none)
Values	(text up to 255 characters)
Key Required	No
Example	Adapter Name = 3C59X_1
Purpose	Specifies a unique name for this adapter.

Frame Type n = <frame type>

Default	(none)
Values	(frame types supported by the driver are found in the driver's LDI file)
Key Required	No
Example	Frame Type 1 = Ethernet_802.2
Purpose	Identifies the network frame type to be used when loading the driver. There can be as many descriptions as there are frame types supported by the driver— n uniquely identifies the frame type (for example, 1, 2, etc.).

Logical Name n = <string>

Default	(none)
Values	(text combining the Frame Type with the Adapter Name)
Key Required	No
Example	Logical Name 1 = 3C59X_1_E82
Purpose	Identifies the name to be used when binding a protocol to a frame type on this adapter. There must be a logical name for each frame type loaded with the driver— n uniquely identifies the frame type (for example, 1, 2, etc.).

Octet Bit Order = <string>

Default	LSB
Values	LSB or MSB
Key Required	No
Example	Octet Bit Order = LSB
Purpose	Specifies the bit order (Least Significant Bit or Most Significant Bit) that this network adapter uses for deciphering the node address.

[NWI:Reserved Adapter *n*] Section

Example	[NWI:Reserved Adapter 1]
Description	This section can be included for each slot in the server.

SLOT = <integer>

Default	(none)
Values	(can be a 5-digit Hardware Instance Number assigned on servers with buses that support detection—such as PCI)
Key Required	No, unless the driver is for an ISA adapter
Example	SLOT = 5
Purpose	Specifies the bus slot that should be reserved. If an adapter is found in this slot, an error is generated.

[NWI:Hotplug System] Section

Driver File = <filename>

Default	(none)
Values	(name of driver)
Key Required	No, unless HotPlug Detection=False
Example	Driver File = CPQSBD.NLM
Purpose	Identifies the driver to use for the Hot Plug system.

[NWI:NetWare Loadable Module] Section

Driver File = <filename>

Default	(none)
Values	(name of NLM)
Key Required	No
Example	Driver File = ROUTE.NLM
Purpose	Identifies the NLM to load during installation. This is typically used for network support NLM programs.

[NWI:File System] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the character-based SYS Volume and Partition screen is displayed.

Allow Volume Properties = <string>

Default	True
Values	True or False
Key Required	No
Example	Allow Volume Properties = True
Purpose	Controls whether the F3 Volume Properties option is displayed.

GUI Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	GUI Prompt = True
Purpose	Controls whether the File System screen is displayed during the graphical portion of the install.

[NWI:Partition *n*] Section

Example	[NWI:Partition 0]
Description	This section allows partitions to be created on specific devices in the system during installation. The devices are specified by the key entries in the section. The zero-based sequence number ($n = 0, 1, 2, 3, \dots$) in the section heading specifies the order in which the partitions are created. The partition on which volume SYS is created must be defined in [NWI:Partition 0].

Device Type = <string>

Default	(none)
Values	IDE or SCSI
Key Required	No
Example	Device Type = IDE
Purpose	Identifies the type of the device the partition is to be placed on.

IDE Device Serial Number = <string>

Default	(none)
Values	(string of characters)
Key Required	No
Example	IDE Device Serial Number = AX8273430930.
Purpose	Specifies the serial number of the device designated by the manufacturer. (It is usually found on a sticker attached to the device.)

IDE Device Channel = <integer>

Default	(none)
Values	1 or 2 or 3 or 4
Key Required	No
Example	IDE Device Channel = 1
Purpose	Identifies the channel on which the device is to be found.

IDE Device Type = <string>

Default	(none)
Values	Master or Slave
Key Required	No
Example	IDE Device Type = Master
Purpose	Specifies the IDE type of the device on the channel.

SCSI Device Adapter Slot = <integer>

Default	(none)
Values	1 to 16
Key Required	No
Example	SCSI Device Adapter Slot = 1
Purpose	Identifies the physical slot number of the SCSI adapter

SCSI Device ID = <integer>

Default	(none)
Values	0 to 15
Key Required	Yes
Example	SCSI Device ID = 0
Purpose	Specifies the ID of the device on the SCSI chain

Partition Type = <string>

Default	NSS
Values	NetWare or NSS or Free
Key Required	No
Example	Partition Type = NSS
Purpose	Identifies the type of partition to be created

Partition Size = <integer> or <ALL FREE SPACE>

Default	(none)
Values	(up to the size of free space on the device in MB)
Key Required	No
Example	Partition Size = 1000
Purpose	Identifies the size of the partition. Note that the number is modified to align with a cylinder boundary. "ALL FREE SPACE" specifies that all remaining free space on the device will be used.

Partition HotFix Size = <integer>

Default	(calculated on Partition Size)
Values	0 to 120 (in MB)
Key Required	No
Example	Partition HotFix Size = 20
Purpose	Identifies the size of the redirection area on the partition

Mirror Partition = <integer>

Default	(none)
Values	(partition number)
Key Required	No
Example	Mirror Partition = 3
Purpose	Identifies the partition that this partition will be mirrored to.

[NWI:Volume *n*] Section

Example	[NWI:Volume 0]
Description	This section can be included for each volume defined on the server. Note that SYS must be Volume 0. This section allows volumes to be created on specific partitions in the system during installation. The partitions are specified by the key entries in the section. The zero-based sequence number (<i>n</i> = 0, 1, 2, 3, ...) in the section heading specifies the order in which the volumes are created. Volume SYS must be defined in [NWI:Volume 0].

Volume Name = <string>

Default	(none)
Values	(valid volume name)
Key Required	Yes
Example	Volume Name = DATA
Purpose	Identifies the name of the volume; follows naming convention found in the NetWare user documentation.

Volume Type = <string>

Default	NSS
Values	NetWare or NSS or Free
Key Required	No
Example	Volume Type = NSS
Purpose	Specifies the type of the volume to be created. Note that volume types must be created on like partition types (e.g., NSS volume on NSS partition).

Block Size = <integer>

Default	(calculated on the size of the first segment of the volume)
Values	4 or 8 or 16 or 32 or 64
Key Required	No
Example	Block Size = 64
Purpose	Identifies the volume's block size. Note that this key does not apply to NSS volumes.

Compression = <string>

Default	True
Values	True or False
Key Required	No
Example	Compression = True
Purpose	Specifies whether compression is enabled on the volume.

Suballocation = <string>

Default	True (on NetWare volume types)
Values	True or False
Key Required	No
Example	Suballocation = True
Purpose	Specifies whether suballocation is enabled on the volume. Note that this key does not apply to NSS volumes.

Data Migration = <string>

Default	False
Values	True or False
Key Required	No
Example	Data Migration = True
Purpose	Specifies whether data migration is enabled on the volume. Note that this key does not apply to NSS volumes.

Mount = <string>

Default	False
Values	True or False
Key Required	No
Example	Mount = True
Purpose	Specifies whether the volume should be mounted during installation. This is useful if additional products and services are to be installed on a volume other than SYS. Note that mounting volumes will take additional time during the server installation. Also, this key will be ignored if GUI Prompt = False is not set in the NW!File System section; this is to avoid a conflict between this key and the mount volumes screen during installation.

Segment *n* Partition = <integer>

Default	(none)
Values	(any value <i>n</i> previously defined in section [NW!Partition <i>n</i>])
Key Required	Yes
Example	Segment 1 Partition = 1
Purpose	Identifies the partition on which the volume segment is to be created. The number of segments <i>n</i> is limited from 1 to 8 for NetWare partitions and must be defined sequentially.

Segment n Size = <integer> or <ALL FREE SPACE>

Default	(none)
Values	(up to free space on a partition in MB)
Key Required	Yes
Example	Segment 1 Size = 1000
Purpose	Specifies the size of the volume segment. "ALL FREE SPACE" specifies that all remaining free space on the partition will be used.

[NWI:Misc] Section

Relogin Password = <string>

Default	(none)
Values	(text)
Key Required	No, unless it is a network installation.
Example	Relogin Password = Novell
Purpose	Specifies the password for the user connection being used while installing across the network. When this section is properly used, the install bypasses the reauthentication screen following the loading of the LAN driver and prior to the preliminary file copy.

[NWI:File Server] Section

NOTE: This is the first section used during the graphical portion of the installation.

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the screen is displayed.

Servename = <string>

Default	(none)
Values	(text up to 47 characters—see NetWare documentation for valid set of characters)
Key Required	Yes
Example	Servename = Novell
Purpose	Specifies the name of the server. Note that a server is brought up with temporary name until a valid Servename is entered.

Server ID Number = <hexadecimal number>

Default	(randomly generated)
Values	00000001-FFFFFFFF
Key Required	Yes
Example	Server ID Number = 01010101
Purpose	Uniquely identifies the server for network communication purposes. Note that this number should not conflict with any existing IPX™ addresses on your network.

[NWI:Protocols] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the protocols screen is displayed.

Single Network Adapter=<string>

Default	False
Values	True or False
Key Required	No
Example	Single Network Adapter=True
Purpose	If this key is set to True then in the [NWI:TCPIP] and [NWI:IPX] sections of the response file the "Logical Name 1" key is automatically filled in with the logical name of the first network card found in the system. The logical name will be bound to the TCPIP and IPX addresses specified in the [NWI:TCPIP] and [NWI:IPX] sections of the response file.

Default IP Frame Typer=<string>

Default	(none)
Values	(Frame types that are supported by a driver are found in the driver's LDI file)
Key Required	No
Example	Default IP Frame Type=Ethernet II
Purpose	Identifies the network frame type to be bound to the IP stack when the "Single Network Adapter" is set to True.

Default IPX Frame Type=<string>

Default	(none)
Values	(Frame types that are supported by a driver are found in the driver's LDI file)
Key Required	No
Example	Default IPX Frame Type=Ethernet 802.2
Purpose	Identifies the network frame type to be bound to the IPX stack when the "Single Network Adapter" is set to True.

[NWI:TCPIP] Section

Logical Name n = <string>

Default	(none)
Values	(name identified in the Network Adapter sections of the response file)
Key Required	No, unless IP is to be bound.
Example	Logical Name 1 = 3C59X_1_EII
Purpose	Identifies the name of the adapter and frame type that the protocol is to be bound to.

IP Address n = <decimal number>

Default	(none)
Values	(valid IP address)
Key Required	No, unless Logical Name is set
Example	IP Address 1 = 130.1.130.1
Purpose	Specifies the IP address to be bound.

Subnet Mask n = <decimal number>

Default	(none)
Values	(valid IP address)
Key Required	No, unless Logical Name is set.
Example	Subnet Mask 1 = 255.255.255.0
Purpose	Specifies the subnet. Divides the IP address into network address and node address.

Gateway n = <decimal number>

Default	(none)
Values	(valid IP address)
Key Required	No
	Gateway 1 = 127.127.0.254
Purpose	Identifies the gateway or router through which this server can communicate outside the subnet.

[NWI:IPX] Section

Logical Name n = <string>

Default	(none)
Values	(name identified in the Network Adapter sections of the response file)
Key Required	No, unless IPX is to be bound
Example	Logical Name 1 = 3C59X_1_E82
Purpose	Identifies the name of the adapter and frame type that the protocol is to be bound to.

IPX Address n = <hexadecimal number>

Default	(address detected by the installation program)
Values	00000001-FFFFFFFF
Key Required	No, unless Logical Name is set
Example	IPX Address 1 = 01010102
Purpose	Specifies the IPX address to be bound.

[NWI:IPCMD] Section

IPX Compatibility = <string>

Default	True
Values	True or False
Key Required	No
Example	IPX Compatibility = True
Purpose	Controls whether SCMD is loaded on this server.

Migration Agent = <string>

Default	True
Values	True or False
Key Required	No
Example	Migration Agent = True
Purpose	Controls whether the Migration Agent (SCMD /MA) is loaded on this server.

CMD Net Number = <string>

Default	(none)
Values	00000001-FFFFFFFF
Key Required	No
Example	CMD Net Number = 01010101
Purpose	Specifies the network number.

Preferred IP Address = <decimal number>

Default	(none)
Values	(valid IP address)
Key Required	No
Example	Preferred IP Address = 130.1.130.1
Purpose	Specifies the IP address.

[NWI:SNMP] Section

Hardware = <string>

Default	(none)
Values	Values (text)
Key Required	No
Example	Hardware = Personal Computer
Purpose	Identification information that is sent with SNMP traps to assist in troubleshooting.

Location = <string>

Default	(none)
Values	(text)
Key Required	No
Example	Location = Building A
Purpose	Identification information that is sent with SNMP traps to assist in troubleshooting.

Contact = <string>

Default	(none)
Values	(text)
Key Required	No
Example	Contact = John Doe
Purpose	Identification information that is sent with SNMP traps to assist in troubleshooting.

Trap Targets TCPIP = <decimal numbers separated by commas>

Default	(none)
Values	(valid IP addresses)
Key Required	No
Example	Trap Targets TCPIP = 127.1.127.3
Purpose	Identifies IP address of a computer to which SNMP traps are sent.

Trap Targets IPX = <MAC address separated by commas>

Default	(none)
Values	(8-character IPX address:12-character node number)
Key Required	No
Example	Trap Targets IPX = C9990111:000001B555555
Purpose	Identifies MAC addresses of a computer to which SNMP traps are sent.

[NWI:DNS] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the DNS screen is displayed.

Domain = <string>

Default	(none)
Values	(text)
Key Required	No
Example	Domain = novell.com
Purpose	Specify a domain.

Nameservers = <decimal numbers separated by commas>

Default	(none)
Values	(valid IP addresses)
Key Required	No
Example	Nameservers = 131.1.131.1, 131.1.131.2
Purpose	Identifies the servers to be used for name resolution.

[NWI:Host Name] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the screen is displayed.

Host Name n = <string>

Default	(none)
Values	(text)
Key Required	No
Example	Host Name 1 = install.novell.com
Purpose	Specifies the host name associated with an IP address already bound.

IP Address n = <decimal number>

Default	(none)
Values	(valid IP address)
Key Required	No
Example	IP Address 1 = 130.1.130.1
Purpose	Specifies the IP address associated with a Host Name. Note that Host Name 1 will be set as the Primary address.

[NWI:Time Zone] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the time zone screen is displayed.

Time Zone = <string>

Default	(none)
Values	(string—see COMOTHR.ILS)
Key Required	Yes
Example	Time Zone = (GMT-06:00) U.S. and Canada Central Time
Purpose	Specifies the standard time zone. Note that the exact string from COMOTHR.ILS (in INSTALL\NLS\4) must be used.

Use Daylight Saving Time = <string>

Default	True, if Time Zone supports Daylight Saving Time
Values	True or False
Key Required	No
Example	Use Daylight Saving Time = True
Purpose	Controls whether daylight saving time is set.

[NWI:Time Synchronization] Section

Default Time Server Type = <string>

Default	(Single if new tree, Secondary if existing tree)
Values	Single, Primary, Secondary
Key Required	No
Example	Default Time Server Type = Single
Purpose	Specifies the time server type.

[NWI:NDS] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the NDS screen is displayed.

Tree Name = <string>

Default	(none)
Values	(text)
Key Required	Yes
Example	Tree Name = Novell
Purpose	Specifies the tree name for either a new tree or an existing tree to install the server into.

New Tree = <string>

Default	False
Values	True or False
Key Required	Yes
Example	New Tree = True
Purpose	Specifies whether the NDS tree to be installed is a new tree or install into an existing tree.

NOTE: This key is only used when Prompt = False.

Server Context = <string>

Default	(none)
Values	(NDS distinguished name)
Key Required	Yes
Example	Server Context = .install.novell
Purpose	Identifies the NDS context that the server is to be installed into.

Add Replica = <string>

Default	(none)
Values	True or False
Key Required	No
Example	Add Replica = True
Purpose	Controls whether a replica is added to the server. This only applies if the server is not one of the first three servers added to an NDS tree (by default the first three servers receive replicas).

Upgrade User Conflict Action = <string>

Default	(none)
Values	Delete, Merge, or Rename
Key Required	No, unless it is an upgrade from NetWare 3.1x
Example	Upgrade User Conflict Action = Merge
Purpose	Determines what action is to be taken during the upgrade of a NetWare 3.1x server when objects of the same name are found during the conversion of the bindery to NDS.

Admin Login Name = <string>

Default	(none)
Values	(text)
Key Required	Yes
Example	Admin Login Name = Admin
Purpose	Specifies the name for the server administrator.

Admin Context = <string>

Default	(none)
Values	(NDS distinguished name)
Key Required	Yes
Example	Admin Context = .install.novell
Purpose	Identifies the NDS context in which the server administrator is to be installed into.

Admin Password = <string>

Default	(none)
Values	(text)
Key Required	Yes
Example	Admin Password = Novell
Purpose	Specifies the password for the server administrator. Note that for security purposes, this password is removed from the response file after NDS is installed.

Admin Language = <integer>

Default	4 (English)
Values	1-100
Key Required	Yes
Example	Admin Language = 4
Purpose	Specifies the language of the server administrator. User objects created by the server administrator will be assigned this language.

Display Summary = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Display Summary = True
Purpose	Controls whether the NDS Summary screen is displayed

[NWI:License] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the license screen is displayed.

Display License Agreement = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Display License Agreement = False
Purpose	Controls whether the license agreement screen at the beginning of the server install is displayed

Install Licenses Later = <string>

Default	False
Values	True or False
Key Required	No
Example	Install Licenses Later = True
Purpose	Specifies that no licenses will be installed on the server. If this key is set to True, all remaining licensing keys will be ignored.

License File = <string>

Default	(none)
Values	(existing DOS path and envelope file name—up to 255 characters)
Key Required	No, unless a license is to be installed
Example	License File = C:\NWSERVER\0000001.NLF
Purpose	Identifies the directory and filename of a license envelope file.

NICI Foundation Key File = <string>

Default	(none)
Values	(existing DOS path and envelope file name—up to 255 characters)
Key Required	No
Example	NICI Foundation Key File = C:\LIC\92942492.NFK
Purpose	Identifies the directory and filename of a region specific cryptography module.

Search For Existing License = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Search For Existing License = False
Purpose	Controls whether the licenses (such as MLA licenses) are searched for in the tree. Used in conjunction with the next key.

Auto Skip If License Found = <string>

Default	False
Values	True or False
Key Required	Yes
Example	Auto Skip If License Found = True
Purpose	Controls whether the license that was found using the previous key is used; this is particularly useful for MLA accounts.

[NWI:Add to Startup] Section

Prepend Line n = <decimal number>

Default	(none)
Values	(decimal number)
Key Required	No
Example	Prepend Line 1 = SET IGNORE DISK GEOMETRY=ON
Purpose	Adds the line to the beginning of the STARTUP.NCF file. If multiple lines are listed, <i>n</i> should increment sequentially.

Append Line n = <decimal number>

Default	(none)
Values	(decimal number)
Key Required	No
Example	Append Line 1 = LOAD NFS.NAM
Purpose	Adds the line to the end of the STARTUP.NCF file. If multiple lines are listed, <i>n</i> should increment sequentially.

[NWI:Append To Autoexec.ncf] Section

Line n = <decimal number>

Default	(none)
Values	(decimal number)
Key Required	No
Example	Line 1 = LOAD MONITOR
Purpose	Adds the line to the end of the AUTOEXEC.NCF file. If multiple lines are listed, <i>n</i> should increment sequentially.

[NWI:Use NCF Settings] Section

Override NCF = <True or False>

Default	(False)
Values	(True or False)
Key Required	No
Example	Override NCF = True
Purpose	During an upgrade, if set to True, the server name is specified in the response file instead of the AUTOEXEC.NCF file.

Performing a Fully Automated Installation

The following parameters must be present to completely automate an installation or upgrade. The syntax and values for the supplementary NetWare installation sections and their associated keys are specified below. For a fully automated installation to work, these sections must appear in the response file in addition to all of the required keys listed in [“NetWare Sections and Keys” on page 33](#).

[Novell:NOVELL_ROOT:1.0.0] Section

closeScreen = <string>

Default	(none)
Values	SilentCloseScreen
Key Required	Yes
Example	closeScreen = SilentCloseScreen
Purpose	When this parameter is set, the final installation screen is not shown.

Reboot = <string>

Default	(none)
Values	True or False
Key Required	Yes
Example	Reboot = False
Purpose	Controls whether the server is restarted after the final screen of the installation is closed.

allowSummary = <string>

Default	True
Values	True or False
Key Required	Yes
Example	allowSummary = False
Purpose	Controls whether the installation Summary screen is displayed.

silent = <string>

Default	False
Values	True or False
Key Required	Yes
Example	silent = False
Purpose	Global key that controls whether the installation runs in silent mode with no user interaction. Some sections do not support this key. If this is the case, use a "prompt=false" key instead.

Automating the Installation of Additional Products and Services

As part of the overall NetWare installation, you can auto-install additional products and services by including a [Selected Nodes] section in the response file. Because this section of the response file is not as easy to configure as the other sections are, we recommended the following:

- 1** Perform a manual installation, selecting the products you want to have installed on the server.
- 2** Modify the resulting response file for use as input to future NetWare installations.
- 3** Add a [Selected Nodes] section to the input response file.

4 Add the following lines under the [Selected Nodes] section heading:

```
Novell:NetWare5:1.0.0=Novell:NetWare50S:5.0.0,Novell:Products:1.0.0,Novell:NW
UpdateGroup:1.0.0
Novell:NetWare50S:5.0.0=Novell:DiskCarver:1.0.0,Novell:Protocols:1.0.0,Novell
:DS_Install:1.0.0,Novell:LicensePrompt:1.0.0,Novell:NW:1.0.0,Novell:NDPS
Server Files:1.0.0
Novell:NW:1.0.0=Novell:Startup:1.0.0,Novell:SYS:1.0.0,Novell:DriverFiles:1.0.
0
Novell:Startup:1.0.0=Novell:StartupDirectory:1.0.0
Novell:SYS:1.0.0=Novell:SYSDirectory:1.0.0,Novell:ETCDirectory:1.0.0,Novell:P
ROFINST_NODE:1.0.0
Novell:DriverFiles:1.0.0=Novell:LANFiles:1.0.0,Novell:SBDFiles:1.0.0
Novell:NDPS Server Files:1.0.0=Novell:NDPS System:1.0.0,Novell:NDPS
Public:1.0.0
Novell:Products:1.0.0=Novell:NICIInstall:1.0.0
Novell:NICIInstall:1.0.0=Novell:NICIModule:1.0.0
Novell:NWUpdateGroup:1.0.0=Novell:NWUpdate:1.0.0
```

NOTE: You can add more lines according to your needs, but these represent the minimum information that must be included in the [Selected Nodes] section.

[Selected Nodes] Section

Prompt = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Prompt = True
Purpose	Controls whether the Additional Products and Services screen is displayed.

Product Selection = <string>

Default	(none)
Values	Default or Web
Key Required	No
Example	Product Selection = Web
Purpose	Specifies which bundle of Additional Products and Services to install. Default will install the Web Services bundle. Web will install the Web Services bundle plus WebSphere* Application Server. To specify a custom bundle of Additional Products and Services, do not include this key, and specify each product as described below.

Novell:Products:1.0.0 = <strings separated by commas>

Default	Novell:NICInstall:1.0.0 NOTE: This NICI install string must be included.
Values	Novell:NDPS:2.0.0 Novell:IpLdapService:3.0.0 Novell:IpCatalogService:1.0.0 Novell:IpWanmanService:1.0.0 Novell:SecuritySASInstall:1.0.0 Novell:PKIInstall:1.0.0 Novell:NICInstall:1.0.0 Novell:RAS:4.1.0 Novell:SMS:1.0.0 Novell:DNS_DHCP:1.0.0
Key Required	Yes
Example	Novell:Products:1.0.0=Novell:NICInstall:1.0.0,Novell:NDPS:2.0.0
Purpose	Specifies the additional products and services to be installed on the server.

Installing Multiple Products on a Server

To install multiple products on a server, make sure that the Novell:Products:1.0.0 key has multiple values, separated by commas as shown in the example above.

Product Keys and Values

In addition to identifying the product in the Novell:Products:1.0.0 key, each product has its own keys and values for the [Selected Nodes] section. These keys and values for each product are listed below. We recommended that you reuse a response file from a previous installation rather than attempting to type these keys and values into the file. If you do not enter them exactly as shown, the NetWare Installation will fail abruptly with no information to help you troubleshoot the problem.

Novell Distributed Print Services (NDPS)

```
Novell:NDPS:2.0.0=Novell:NDPS Server Files:1.0.0,Novell:NDPS Resource
Files:1.0.0
Novell:NDPS Resource Files:1.0.0=Novell:NDPS Banner:1.0.0,Novell:NDPS
Font:1.0.0,Novell:NDPS Prndef:1.0.0,Novell:NDPS Prndrv:1.0.0
Novell:NDPS Prndrv:1.0.0=Novell:NDPS Prndrv W31:1.0.0,Novell:NDPS Prndrv
W95:1.0.0,Novell:NDPS Prndrv NT4:1.0.0
```

LDAP Services

```
Novell:SecuritySASModule:1.0.0=Novell:SASFiles:1.0.0
Novell:PKIModule:1.0.0=Novell:PKIFiles:1.0.0
```

NDS Catalog Services

```
Novell:IpCatalogService:1.0.0=Novell:DfgCatalogService:1.0.0
```

WAN Traffic Manager Services

```
Novell:IpWanmanService:1.0.0=Novell:DfgWanmanService:1.0.0
```

Secure Authentication Services

```
Novell:SecuritySASInstall:1.0.0=Novell:SecuritySASModule:1.0.0,Novell:PKIModu
le:1.0.0,Novell:NICIModule:1.0.0
Novell:SecuritySASModule:1.0.0=Novell:SASFiles:1.0.0
Novell:PKIModule:1.0.0=Novell:PKIFiles:1.0.0
```

Novell PKI Services

Novell:PKIInstall:1.0.0=Novell:PKIModule:1.0.0,Novell:NICIModule:1.0.0
Novell:PKIModule:1.0.0=Novell:PKIFiles:1.0.0

Novell Internet Access Server

Novell:RAS:4.1.0=Novell:RAS Server
Files:1.0.0,Novell:SVCDEF_NODE:1.0.0,Novell:SupportedOS:1.0.0,Novell:UpgradeF
rom:1.0.0
Novell:RAS Server Files:1.0.0=Novell:RAS System Connect:1.0.0,Novell:RAS System
Connect Scripts:1.0.0,Novell:RAS Public:1.0.0

Storage Management Services

Novell:SMS:1.0.0=Novell:SMSFiles:1.0.0
Novell:SMSFiles:1.0.0=Novell:SMSSystemFiles:1.0.0,Novell:SMSPublicFiles:1.0.0

Novell DNS/DHCP Services

No additional keys and values are used for the installation of this service.

Additional Services

Two of the additional services available with NetWare, LDAP Services and Novell® DNS/DHCP Services, have data input screens for their configuration. These services have response file sections that must be included in addition to the keys and values mentioned above.

NOTE: Be sure to use the proper case (upper or lower) when entering any of these keys and values.

[LDAP] Section

prompt = <string>

Default	(none)
Values	true or false
Key Required	Yes
Example	prompt=false
Purpose	Controls whether the LDAP configuration screen is displayed.

adminID = <string>

Default	(none)
Values	(NDS distinguished name)
Key Required	Yes
Example	adminID=.CN=admin.O=install
Purpose	Identifies the Admin name and NDS context; this should correspond with the Admin Login Name and Admin Context identified in the NWI:NDS section of the response file. Note the case of the characters in the string.

installCatalog = <string>

Default	(none)
Values	true or false
Key Required	Yes
Example	installCatalog=false
Purpose	Controls whether an LDAP catalog is installed. Corresponds to the question: Enable use of LDAP catalog?

useCatalogOnly = <string>

Default	(none)
Values	true or false
Key Required	Yes
Example	useCatalogOnly=false
Purpose	Controls whether the LDAP catalog is used exclusively for searching. Corresponds to the LDAP screen prompt: Catalog Usage for Searching.

Prompt = <string>

Default	None
Values	true or false
Key Required	Yes
Example	Prompt=false
Purpose	Controls whether the DNS/DHCP configuration screen is displayed.

TreeName = <string>

Default	(none)
Values	(text)
Key Required	Yes
Example	TreeName=Novell
Purpose	Specifies the NDS tree name in which DNS/DHCP Services will be installed.

UserName = <string>

Default	(none)
Values	(NDS distinguished name)
Key Required	Yes
Example	UserName=.CN=admin.O=install
Purpose	Identifies the Admin name and NDS context; this should correspond with the Admin Login Name and Admin Context identified in the NWI:NDS section of the response file. Note the case of the characters in the string.

ExtendDNIPSchema = <string>

Default	(none)
Values	true or false
Key Required	Yes
Example	ExtendDNIPSchema=true
Purpose	Controls whether the schema is extended for DNS/DHCP Services. Note that this should be set to true.

LocatorNDSText = <string>

Default	(none)
Values	(NDS distinguished name)
Key Required	Yes
Example	LocatorNDSText=O=install
Purpose	Identifies the NDS context that the Locator Object is to be installed into.

GroupNDSText = <string>

Default	(none)
Values	(NDS distinguished name)
Key Required	Yes
Example	GroupNDSText=O=install
Purpose	Identifies the NDS context that the Group Object is to be installed into.

RootSrvrNDSText = <string>

Default	(none)
Values	(NDS distinguished name)
Key Required	Yes
Example	RootSrvrNDSText=O=install
Purpose	Identifies the NDS context that the RootSrvr Zone is to be installed into.

In addition to the DNS/DHCP keys identified above, there must also be a line in the [Settings] section with the entry: Novell:DNS_DHCP:1.0.0=

CD Boot and the Response File

There are two options available for passing a response file into the NetWare installation: using the /RF switch at the command line, or from the Install Options screen.

If you start the install by booting directly to the NetWare CD, you cannot pass in the response file automatically unless you have a RESPONSE.TXT file in the C:\NWUPDATE directory. When the NetWare CD is booted, the startup utility checks for a RESPONSE.TXT file in the C:\NWUPDATE directory. If such a file exists, the installation program bypasses the DOS partitioning utility and uses RESPONSE.TXT as the input response file.

Customizing the Installation Using Install Scripts

In NetWare, install scripts are supported by the NWCONFIG utility and the NetWare installation system.

NOTE: For more information on using install scripts, see [Automating the NetWare Installation with a Response File \(http://www.developer.novell.com/research/appnotes/1998/december/a1frame.htm\)](http://www.developer.novell.com/research/appnotes/1998/december/a1frame.htm) and [More About Automating the NetWare Installation with a Response File \(http://www.developer.novell.com/research/appnotes/1999/february/a3frame.htm\)](http://www.developer.novell.com/research/appnotes/1999/february/a3frame.htm).

There are two places in the NetWare installation where you can use install scripts:

- ♦ At the end of the preliminary file copy (just prior to the launching of the graphical portion of the install). An install script executed here can be used for copying files from the DOS partition to the SYS volume.
- ♦ At the end of the NetWare installation. It is called right after you answer AOK@ or ANo@ on the closing screen and before the install cleanup process. This script is useful if you want to manage files and launch NLM programs (for example, those that install other products) as part of the NetWare installation.

The following response file syntax is used to run install scripts during the NetWare installation:

[NWl:Install Script] Section

Script Location = <string>

Default	None
Values	(existing DOS path up to 255 characters)
Key Required	No
Example	Script Location = C:\NWUPDATE\PRECOPY.IC?
Purpose	Identifies the filename and path of an Install Script that will be executed at the end of the preliminary file copy (prior to the launching of the graphical portion of the install).
	NOTE: Usage of the ? wildcard in the extension of the filename will suppress an error if the specified file does not exist.

Support Pack Script = <string>

Default	Support Pack Script = C:\spack\silent.ics
Values	(existing DOS path up to 255 characters)
Key Required	No
Example	If the support pack image is located on the C: drive, use this path: Support Pack Script=c:\nw51sp1\spack.ips e=c:\facterr.log s=c:\nw51sp1 If the support pack image is on a mounted CDROM, use this path: Support Pack Script=NW51:\spack.ips e=c:\err.log s=NW51:\ If the support pack image is on a remote server, use this path: Support Pack script=prv-athena\images:nw5\cobra\sp1 128.524\spack.ips TRANSPORT=IPX u="SITESTER2" a=01010155:000000000001:0451 DS c="CN=SITESTER2.OU=INSTALL.OU=DEV.O=NOVELL" z=PRV-ATHENA-TREE e=C:\err.log s=PRV-ATHENA\IMAGES:NW5\COBRA\SP1 128.524
Purpose	Identifies the filename and path of an Install Script that will be executed at the end of the install.

Close Script = <string>

Default	None
Values	(existing DOS path up to 255 characters)
Key Required	No
Example	Script Location = SYS:\OTHER.ICS
Purpose	Identifies the filename and path of an Install Script that will be executed when the final screen of the NetWare server installation is closed. NOTE: This script is executed just prior to some housekeeping that is done by the Close Screen routine.

Performing a Factory Install

A Factory Install can reduce the complexity and time spent on an installation. Much of the hardware configuration and file copy is done in the Factory so that you only need to use the graphical portion of the NetWare installation to complete the on-site configuration. Because the network operating system files are pre-copied to the server, installation time is reduced to a few minutes.

A Factory Install splits the installation of NetWare into two phases:

- ♦ Phase 1 performs the disk detection, disk partitioning, volume SYS creation, and file copy portions of the install. This phase is meant to be performed in a factory or configuration center.
- ♦ Phase 2 focuses on user configuration. It includes the setting of the server name, protocol binding, creation of volumes other than SYS, and configuration of time zone, NDS, licensing, and other products. This phase is meant to be performed by the customer at the server's permanent location.

Once Phase 1 is completed, the machine should be rebooted or powered off. When the machine is powered on and the server is started, the AUTOEXEC.NCF file will launch Java* for Phase 2 of the installation.

A Factory Install is implemented with the response file sections below. A default Factory Install response file can be created by combining the FACTORY.TXT and RESPONSE.TXT files found in the \INSTALL directory of the NetWare Operating System CD.

he Preinstall key of the [NWI:Factory] section is the primary key that directs the NetWare Installation to perform a factory install. The Precopy key of the other sections specifies whether the file group should be recopied during the final file copy routine of the NetWare Installation. If Precopy=True, the files will be verified, but not copied. The Installation will appear, however, as if it is copying the files because you will see each file name displayed in the copy status box.

NOTE: The NetWare CD must be inserted in Phase 2 of the Factory Install in order to perform this file verification.

All other required keys for an automated install must also be included in the response file. See [“Performing a Fully Automated Installation” on page 78](#) for more information.

[NWI:Factory] Section

Preinstall = <string>

Default	True
Values	True or False
Key Required	Yes
Example	Preinstall = True
Purpose	Controls whether the Factory Install option of the NetWare installation is invoked. If Preinstall=True, the remaining keys are checked.

Copy Products to SYS = <string>

Default	False
Values	True or False
Key Required	No
Example	Copy Products to SYS = True
Purpose	Controls whether the products directory of the NetWare Installation CD is copied to volume SYS so that products can be selected and installed during Phase 2 without the need for a NetWare Operating System CD.

Remove Directory = <local path>

Default	(none)
Values	(existing DOS path up to 255 characters)
Key Required	No
Example	Remove Directory = SYS:\PRODUCTS
Purpose	Removes a directory from the system at the end of Phase 2.

[Novell:StartupDirectory:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the files in the \STARTUP\NLS directory of the install image and destined for the C:\Startup_Directory\NLS directory are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

[Novell:SYSDirectory:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the files in the \STARTUP\NLS directory of the install image and destined for the C:\Startup_Directory\NLS directory are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

[Novell:ConfigDirectory:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the files in the \CONFIG directory of the install image, destined for volume SYS, are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

[Novell:LANFiles:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the LAN files in the \DRIVERS\LAN directory of the install image, destined for the SYS:SYSTEM directory, are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

[Novell:SBDFiles:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the files in the \DRIVERS\SBD directory of the install image, destined for the SYS:SYSTEM directory, are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

[Novell:portalzip:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the files in the zip file destined for volume SYS are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

[Novell:Rconjzip:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the files in the zip file, destined for volume SYS, are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

[Novell:Perl5zip:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the files in the zip file, destined for volume SYS, are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

[Novell:beanszip:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the files in the zip file, destined for volume SYS, are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

[Novell:nscriptzip:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the files in the zip file, destined for volume SYS, are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

[Novell:scripteszip:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the files in the zip file, destined for volume SYS, are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

[Novell:console1zip:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the files in the zip file, destined for volume SYS, are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

[Novell:ldapzip:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the files in the zip file, destined for volume SYS, are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

[Novell:wanmanzip:1.0.0] Section

Precopy = <string>

Default	True
Values	True or False
Key Required	No
Example	Precopy = True
Purpose	Controls whether the files in the zip file, destined for volume SYS, are copied in Phase 2. If Precopy = True, the files are not copied again in the final file copy routine.

Install Command Line Options

The following command line options that can be used when initiating the installation executable.

/SERVER_LOG = <string>

Default	(none)
Values	(existing DOS path up to 255 characters)
Key Required	No
Example	Install /LOG=C:\TMP\ERROR.LOG
Purpose	Designates where an installation log file will be created.

/IIPX <decimal number> or /SERVER_ID <hexadecimal number>

Default	(none)
Values	1 - FFFFFFFF
Key Required	No
Example	Install /IIPX 38483933 or Install\SERVER_ID 38483933
Purpose	Allows a specific internal net address to be used for the server being installed.

3

Installation Scripts for NetWare

WARNING: This document describes software that is subject to change. Novell® intends to keep it as current as possible, but the user must assume any inherent risk in developing or maintaining code based on the information in this document. Novell may discontinue or decline to support any software feature described within this document at any time.

This chapter describes the installation script support for NetWare®. NetWare installation scripts let you:

- ♦ Alter or extend the NetWare pre-packaged installation process.
- ♦ Install additional products or services onto a NetWare server after the operating system has been installed.

Using NetWare Installation Scripts

NetWare installation scripts in NetWare 6 are processed by the NWCONFIG.NLM program.

NOTE: NetWare 4 uses INSTALL.NLM to process script commands.

Script Files

Script files are ASCII text files. They can have any eight-character name with one of the following extensions:

Extension	Type of File
.IPS	Individual product installation
.ICS	Common functionality between scripts or non-language specific scripts
.ILS	Language-specific functionality

Launching a Script File

- 1** At the server console, enter **NWCONFIG . NLM**.
- 2** Click Products Options on the Configuration Options screen.
- 3** Click Other Installation Actions menu > Install a product not listed.
- 4** Press F3, and then specify the directory path to the script file.

The directory path is first checked for an .IPS file. If only one .IPS file exists, it is executed. If more than one exists, only the first one found is executed. If there is no .IPS file, PINSTALL.NLM will be loaded and executed. The first @Other...@EndOther descriptor found in the .IPS file is displayed so that you can confirm the product being installed.

The NetWare install program also loads any file that contains the command line parameter “B=”. For example, a script can be launched by entering **LOAD NWCONFIG b=A:\myscript . IPS** (where *myscript* stands for the name of your .IPS file).

Using a Script with NetWare 6

There are two points in the installation where scripts can be launched:

- ♦ At the end of the preliminary file copy just prior to the launching of the graphical portion of the installation.
- ♦ At the end of the installation.

See Using a Response File with NetWare for more information.

The NetWare installation program uses one installation script (NETWARE.ILS) during the text-based file copy. You can modify this script file to copy additional files or launch additional processes, but we do not recommend it.

Descriptors and Commands

This section describes the descriptors and commands found in NETMAIN.ILS and other installation script files. The product installation script files you write contain the same types of descriptors and commands as those in NETMAIN.ILS.

A descriptor is a keyword preceded by the @ character. The installation NLM scans the descriptors and uses them to build linked lists and menus in memory.

Descriptors

- ♦ Describe a configuration or presentation, but do not specify a procedure or order.
- ♦ Are typically block-oriented (with an @Command and an @EndCommand statement), although some are single-line.
- ♦ Are declarative in nature.
- ♦ Cannot be nested.

A command is a keyword not preceded by the @ character. Commands are

- ♦ Procedural, describing the method and order of installation (creating directories, copying files, etc.).
- ♦ Usually grouped within an @FileSet...@EndFileSet descriptor block (although they can also exist independently).
- ♦ Executed in order, according to the script file.

Script files can be natural-language-enabled by using text within double quotes (in-line text). Such text is designated for language translation, including text that will be displayed in menu items, help text, etc.

Syntax Conventions

- ♦ Commands and arguments are not case-sensitive, but prompt strings are.
- ♦ A script parser recognizes the following special characters:

= { } () , : - ; > < ! []

If a special character is used within a name, the entire name must be surrounded by double or single quotation marks.

- ♦ ANSI escape sequences are recognized by the parser within double or single quotes. For example, '\\', '\n', and '\t' represent a backslash, a new line, and a tab, respectively.
- ♦ A NULL character (ASCII value 0) is not allowed anywhere in the file.

Comments

Syntax

```
; <text>
```

Description

A comment (semicolon followed by text) exists for documentation purposes only—it does not invoke a script file operation. Comment characters through the end of a line are read and discarded.

Example

```
; THIS IS A COMMENT
```

Descriptors

@CDName

Syntax

```
@CDName <name>
```

Description

@CDName specifies the name of the CD-ROM volume being installed. This name is passed to CDROM.NLM in a MOUNT command (CD MOUNT <name>) to mount the CD-ROM as a NetWare volume. This descriptor should only be used in a script on a CD-ROM. It should not be used in a diskette drive installation script. Copy CDROM.NLM to the STARTUP directory as specified in the BOOT fileset.

Example

```
@CDName NETWARE5
```

The installation will use the string NETWARE5 when trying to mount the CD-ROM as a NetWare volume. After successfully loading CDROM.NLM, it will issue CD MOUNT NETWARE5 at the system console.

@DeletePartition

Syntax

@DeletePartition <comma-separated list of partition types>

Description

@DeletePartition deletes the existing partitions that you specify. In contrast, the installation NLM's automatic partition creation deletes (by default) existing partitions of the first two types listed below. In both cases, all active partitions are left untouched.

Partition Type	Description	Deleted?
64	NetWare 286	Yes
65	NetWare 386	Yes
01	DOS, 12-bit FAT	No
04	DOS, 16-bit FAT	No
05	Extended partition	No
06	DOS Huge partition	No

If any of these partitions should not be deleted, or if additional partitions need to be added, use @DeletePartition to replace the list.

Example

If the following appears in NETMAIN.ILS, only NetWare 386 partitions are eligible for deletion:

@DeletePartition 65

Syntax

```
@Driver
  Help: "Help description for finding drivers"
  [Dir: <DSK | LAN>, <subdirectory name>, <vol label>,
    <disk description>]
  [Dir: <DSK | LAN>, <subdirectory name>, <vol label>,
    <disk description>]
  ...
@endDriver
```

Description

@Driver specifies help for finding drivers in maintenance-mode installations, or finding disks and directories that contains drivers. <subdirectory name> specifies the directory to read. For floppy or network installations, the subdirectory will typically be NULL. For a CD-ROM, the subdirectory will usually be the common directory where drivers are found. <vol label> is the corresponding media volume name, and <disk description> specifies the printed name on the media that contains the included file. Use @Driver in the NETMAIN.ICS file.

Variable	Description
<subdirectory name>	Specifies the directory to read. For floppy or network installations, the subdirectory is typically NULL. For a CD-ROM, the subdirectory is usually the common directory where drivers are found.
<vol label>	Specifies the name of the corresponding media volume.
<disk description>	Specifies the printed name on the media that contains the include file.

Example

@Driver

Help: "If installing from a floppy, disk drivers will be on disk NetWare-2 and LAN drivers will be on disk NetWare-3. If installing from CDRom, all drivers will be in the directory <cdrom drive>:\NW40\SERVER\DRIVERS."

Dir: DDSK, '', 'NETWARE-2', 'NetWare-2'

Dir: LAN, '', 'NETWARE-3', 'NetWare-3'

@EndDriver

Disk NetWare-2 will be scanned for .DSK and .DDI files; disk NetWare-3 will be scanned for .LAN and .LDI files.

@FileSet

@EndFileSet

Syntax

@FileSet

Description: "...[fileset description]..."

Class: {MANDATORY | CORE | OPTIONAL | OPTIONAL_OFF | BOOT}

Name: <text name - no spaces allowed>

Bytes: <total transfer size for this fileset>

[DiskBytes: <total disk space for this fileset>]

[Attribute: <attribute1>, <attribute2>]

[Flags: <flags>]

<fileset commands...See "Syntax" on page 104.>

@EndFileSet

Description

@FileSet specifies a logically similar group of files to be copied and the necessary commands for copying and installing those files.

The Description and DiskBytes information for OPTIONAL and OPTIONAL_OFF classes of filesets is displayed in a menu before copying. The description for all filesets are displayed during the file copy. Bytes are used to update a status bar representing the total bytes to copy for all selected filesets, which is used in displaying the status bar.

Class specifies how the fileset will be used:

File	Action
MANDATORY	Always executed.
CORE	Always copied in a sequential install, but optionally copied in the selective install/maintain mode.
OPTIONAL	Displayed to the user for selection. They are defaulted to on (selected for copy).
OPTIONAL_OFF	Displayed for the user to choose, but are defaulted to off.
BOOT	Copied, depending on the kind of installation and whether the server was launched from the directory that the user is installing to.

For all classes, as the files are copied, the file group status is also displayed, including the file being copied and the percent of all the filesets that have been completed.

Name is used to relate logical filesets together, even when they are declared in different included files. If multiple filesets exist with the same logical name, there can be only one description and one class for all of them. For example, if multiple filesets with the name OS2 are declared, and the class is OPTIONAL, only one description entry for the OS2 files is presented for the user to select. If the user selects it, all filesets with the name OS2 are copied.

BOOT files are files such as SERVER.EXE, SERVER.MSG, NWCONFIG.NLM, NWCONFIG.MSG, NUT.NLM, and NUT.MSG. The BOOT filesets are for internal use only: product files should not have any BOOT fileset declarations. Boot files cannot be compressed or renamed.

Attribute value indicates the final file attributes. The default value for attribute1 is 00060081 (Read Only, Shareable, Rename Inhibit, Delete Inhibit).

For a DOS file:

Attribute1	Meaning
00000001	Read Only
00000002	Hidden
00000004	System
00000008	Volume Label

For a NetWare file:

Attribute1	Meaning
00000001	Read Only
00000002	Hidden
00000004	System
00000008	Execute
00000010	Subdirectory
00000020	Archive
00000080	Shareable
00000700	Smode
00001000	Transaction
00004000	Read Audit
00008000	Write Audit
00010000	Immediate Purge
00020000	Rename Inhibit
00040000	Delete Inhibit
00080000	Copy Inhibit

The meaning for Attribute2 is 00000001 (do not decompress or process file). The default for Attribute2 is zero, which should be used in all usual circumstances.

Flag	Meaning
00000001	Do only for a custom install.
00000002	Do in first-phase copy (bit reset = second-phase).
00000004	Do only if NetWare for OS/2*.
00000008	Do only if native (not SFT III™ or NetWare for OS/2).
00000010	Do only if SFT III.
00000020	Do only for a simplified installation.
00000040	Do only for maintenance mode.
00000080	Do only for upgrade.
00000100	Do only if installing from front end (NWNSTLL.EXE).
00000200	Do only if not installing from front end (NWNSTLL.EXE).

Example

```

@FileSet
  Class: CORE
  Name: SYSTEM_FILES
  Description: "System Files"
  Bytes: 10192463
  CopyToServer 'SYSTEM', '.*', 'SYSTEM-1', "NetWare
System-1 Files"
@endFileSet

```

In this example, *.* files are copied from volume SYSTEM-1:, and the percent of complete status for this fileset is displayed during copying.

@IncludeFile
@EndIncludeFile

Syntax

```
@IncludeFile
  File: <filename>
    [DiskDescription: "...[disk description]..."]
    [DiskVolume: 11 char vol name>]
@EndIncludeFile
```

Description

@IncludeFile specifies a file (<filename>) with additional commands to parse and execute. **DiskDescription** specifies the printed name on the media that shows where the include file is located; **DiskVolume** is the corresponding media volume name.

The command file's directory is searched first. If the include file is not there, the specified disk volume is checked. If <filename> is a <path>\<file> combination, the command file directory is checked first for <file>, then the disk volume at the <path> offset is checked. If <file> includes wildcard characters, all files matching the pattern are included. If the filename has wildcards but no files match, none are included, and no error results. If the filename does not have wildcards, and the file is not present, an error occurs. If the filename is in single quotes and contains % {NWLANG}, % {NWLANG} is replaced by the language number (4=English).

Example

For the NETMAIN.ILS file, where NETMAIN.ICS is not in the same directory as NETMAIN.ILS:

```
@IncludeFile
  File: NETMAIN.ICS
  DiskDescription: '[1]'
  DiskVolume: SYSTEM-1
@EndIncludeFile
```

The file is parsed just after the **@EndIncludeFile** statement. If the installation cannot find NETMAIN.ICS in the directory where NETMAIN.ILS is, it prompts for the CD, then reads and parses NETMAIN.ICS from the CD.

@MessageFile
@EndMessageFile

Syntax

```
@MessageFile  
  File: <filename>  
  [Version: <message file version number>]  
@EndMessageFile
```

Description

@MessageFile specifies a file, usually with the extension .MSG, containing message strings. It is typically located in the same directory as the script file or in an NLS subdirectory. When *<message file version number>* name variables are encountered when the remainder of the script file is parsed (including **@Include** files), the symbols are substituted with definitions from the message file.

The search order of message files is:

1. The current directory.
2. The NLS directory corresponding to the current language.
3. The default definitions of *<message file version number>* “string.”

The Version number is eventually used to synchronize the script file with the messages. If no version is specified, version checking is not performed. Currently, no version checking is performed, regardless of whether the **@Version** descriptor is present.

Example

Using the NETMAIN.ILS file (in the same directory as NETMAIN.MSG):

```
@MessageFile  
  File: NETMAIN.MSG  
@EndMessageFile
```

NETMAIN.MSG is read into memory and used to dereference *<message file version number>* strings.

@StartAppObject
@EndAppObject

Syntax

```
@StartAppObject
  AppPlatform: <Supported Platforms>
  AppName: <Name of the object to create>
  AppPath: <UNC Path to the executable>
  [AppDescription: "...Text..."]
  [AppContact: <List of contacts>]
  [AppMapping: <List of drive mappings>]
  [AppFlags: <>]
  [AppIcon: <Filename of Icon>]
  [AppCaption: "...Text..."]
  [AppParameters: <List of Parameters for AppPath>]
  [AppPrinter: <Printer Ports>]
  [AppShutdownScript: <Filename of Script>]
  [AppStartupScript: <Filename of Script>]
  [AppWorkingDir: <Startup directory for App>]
  [AppUser: <List of users>]
  [AppAdminNotes: "...Text..."]
  [AppFaultTolerance: <List of fallover apps>]
  [AppLoadBalancing: <List of load balancing apps>]
@endAppObject
```

Description

Use @StartAppObject to create NDS objects for use with the Novell® Application Launcher™ (NAL) product. It is used with NetWare for Small Business.

Variable	Description
AppPlatform	The list of supported platforms the Application object can run on.
AppName	The NDS name of the object as viewed in NetWare Administrator.
AppPath	The UNC path and filename of the executable to be launched by the object.
AppDescription	The description that shows on Novell Application Launcher.

Variable	Description
AppContact	The list of usernames to contact for resolving issues with the Application object.
AppMapping	A list of drive mappings that are made for the application to run correctly.
AppIcon	The filename and location of the applications icon.
AppWorkingDir	The startup directory for the application.
AppUser	A list of users authorized to run the application.

Example

```

@StartAppObject
  AppPlatform: 3x 95 NT
  AppName: "Netscape Install"
  AppPath: "SYS\\PUBLIC\\NETSCAPE\\NTSCINST.EXE"
  AppCaption: "Netscape Install"
  AppDescription: "Install the Netscape Internet browser"
  AppContacts: admin
  AppFlags: "No Cleanup"
  AppIcon: "sys:public\\netscape\\netscape.ico"
  AppWorkingDir: "sys\\public\\netscape"
  AppUsers: "All Users" Action Standard Desktop
@EndAppObject

```

This example creates an NDS Application object named Netscape* Install. When NAL is run, this object will let the user install it to their desktop.

```

@Other
@EndOther

```

Syntax

```

@Other
  Description: "...[text]..."
  [DiskDescription: "...[disk description]..."]
  [DiskVolume: <11 char vol name>]
  [File: <filename>]
  [Flags: <flags>]
@EndOther

```

Description

Description is the menu description displayed for the @Other configuration option. This label must be first in the set of labels for a particular @Other option.

File specifies the *.IPS file to execute, or the NLM to load to install the @Other option.

DiskDescription is the prompt name that will be displayed to the user to prompt for another diskette.

DiskVolume is the volume name for the disk specified in DiskDescription. If the DiskVolume label is present, the user is prompted for the specific volume using DiskDescription from drive A: (the user can change the drive). This continues until the file is found or the user cancels. If no DiskVolume is present, Install prompts for another diskette in drive A: and continues until the file is found (if File is present) or the user cancels. If File is not specified, installation looks for any *.IPS or PINSTALL.NLM files.

Flag	Meaning
00000001	Load product environment (clib, btrieve, product.dat).
00000002	Product included in product box (NETMAIN.ILS description).
00000004	Display product should be displayed in simplified installation.
00000008	Display product only in simplified installation.
00000010	Display product only in maintenance installation.
00000020	Display product only in upgrade.
00000040	Display product only in NetWare for OS/2 install.
00000080	Display product only in native installation.
00000100	Display product only in SFT III installation.
00000200	Display product only if started from front end (NWNSTLL.EXE).
00000400	Display product only if not started from front end (NWNSTLL.EXE).

If the other filename extension is .IPS, the file is assumed to be a script and is interpreted. If the other filename extension is .NLM, the file is loaded and executed as an NLM.

Example

@Other

Description: "Install NetWare for Macintosh"

DiskDescription: 'NWM System 1'

DiskVolume: 'MAC-1'

File: PINSTALL.NLM

Description: "Install TCP/IP Protocol"

DiskDescription: 'TCPIP System 2'

DiskVolume: 'TCPIP-2'

File: TCPIP.IPS

@EndOther

The Install NetWare for Macintosh* and Install TCP/IP Protocol menu items are displayed. If NetWare for Macintosh is selected, the user is prompted for the NWM System 1 CD, then PINSTALL.NLM on volume MAC-1: is executed. If TCP/IP is selected, the user is prompted for the TCPIP System 2 CD, then the command file TCPIP.IPS is interpreted.

@SyntaxVersion

Syntax

@SyntaxVersion <major version>.<minor version>

Description

The SyntaxVersion string represents the version of the script file parser. The SyntaxVersion string should be present for all script files, and the syntax version of the parser must match that of the file.

Example

@SyntaxVersion 1.02

The internal syntax string in the installation utility will be compared with this string. If they do not match, the installation will prompt for a different file. All included scripts with a @SyntaxVersion descriptor will be checked for matching version strings (see “@IncludeFile @EndIncludeFile” on page 111).

@StartSchemaMod
@EndStartSchemaMod

Syntax

```
@StartSchemaMod
  SchemaFileName: <Filename>, <Description>
@EndSchemaMod
```

Description

@StartSchemaMod lets NDS schemas be extended through installation scripts.

SchemaFileName specifies the filename for the schema file, along with a Description for displaying to the screen during the modification.

Example

```
@StartSchemaMod
  SchemaFileName: "sys:\\system\\schema\\nwadmin.sch",
  "NetWare Administrator"
@EndSchemaMod
```

In this example, the NWADMIN.SCH file extends the NDS schema and displays "NetWare Administrator" on the screen during the installation of Directory Services.

@TimeZone
@EndTimeZone

Syntax

```
@TimeZone
  Description: <tz description>
  Standard: <tz abb.>, <tz adj.>
  [Daylight: <dst abb.>, <dst adj.>]
  [DSTStart: <start rule>, <seq number>, <day number>,
  <weekday number>, <month number>, <time>]
  [DSTEnd: <end rule>, <seq number>, <day number>,
  <weekday number>, <month number>, <time>]
@EndTimeZone
```

Description

Description specifies a time zone description to be displayed to the user during time services installation.

Standard specifies information to be displayed to the user once the time zone has been selected. This includes the time zone abbreviation and the adjust +/- x:xx:xx from GMT (Greenwich Mean Time) or UTC (Universal Coordinated Time).

If Daylight exists, it specifies that daylight savings time exists for part of the year. It also specifies the daylight abbreviation, and the adjust +/-x:xx:xx from standard time.

DSTStart and DSTEnd specify the rule (w for weekday of month or d for day of month), the sequence number (1-relative), day number (1-relative), weekday number (1-relative), month number (1-relative), and time on a 24-hour clock for daylight savings time.

Sequence number means:		
1	First	(ignore day number)
2	Second	(ignore day number)
3	Third	(ignore day number)
4	Fourth	(ignore day number)
5	Fifth	(ignore day number)
6	Last	(ignore day number)
7	>= day number	
8	<= day number	

Example

```
@TimeZone
  Description: "United States, Mountain Time Zone",
  Standard: "MST", '7:00'
  Daylight: "MDT", '+1:00'
  DSTStart: w, 1, 1, 1, 4, '2:00'
  DSTEnd: w, 6, 1, 1, 10, '2:00'

  Description: "United States, Central Time Zone",
  Standard: "CST", '6:00'
  Daylight: "CDT", '+1:00'
  DSTStart: w, 1, 1, 1, 4, '2:00'
  DSTEnd: w, 6, 1, 1, 10, '2:00'
@endTimeZone
```

Two time zone descriptions are displayed. When one is selected, the time parameters are filled in according to the above information, and the user can verify or edit them.

@TranslateModule

@EndTranslateModule

Syntax

```
@TranslateModule  
  <old driver name1>,<new driver name1>,  
  <old driver name2>,<new driver name2>,  
  ...  
@EndTrandlateModuel
```

Description

@TranslateModule is used internally by NETMAIN.ILS. It specifies that a disk or LAN driver name has been changed for the previous release. The name will be changed in the STARTUP.NCF or AUTOEXEC.NCF file during an upgrade.

@Version

Syntax

```
@Version <major version>.<minor version>
```

Description

The @Version string represents the version of the script file (and its corresponding script data). For the NETMAIN.ILS script file, @Version must be greater than or equal to the expected version of the installation NLM. If any included script files contain version numbers, all the numbers must match. @Version should be incremented each time a new script is released.

In product scripts, the version string is entirely optional. A version string in a product script is not compared with the installation NLM, but all included product scripts must have matching version strings.

Example

@Version 1.01

The version string in the installation is compared with this version string. If they do not match, the installation prompts for a different file. All included scripts with a @Version descriptor will be checked for matching version strings (see “@IncludeFile @EndIncludeFile” on page 111).

Commands

Command

Syntax

Command *<command handler name>*

Description

Command specifies the name of an optional command handler for commands not included in this file. The command handler name must be eight characters or less and correspond to the name of an NLM that exports external command entry points.

Example

Command ICMD.NLM

ICMD.NLM provides external command support (see “[External Command Syntax](#)” on page 126). It supports the command syntax described in this document, plus additional commands.

CopyDriverToServer

Syntax

CopyDriverToServer *<target_directory_path>*, *<file_spec>*,
<source_volume>, *<source_description>*

Description

CopyDriverToServer replaces driver files in *<target_directory_path>* with new driver files. The source files are assumed to be those on the distribution CD (which might have been copied to a user-specified directory).

<file_spec> is the name of the file to be copied, and can be of the form *.LAN, *.DSK, *<directory>*/*.LAN or *<directory>*/*.DSK. *<source_volume>* specifies the name of a diskette volume label and *<source_description>* specifies the string used to prompt for the diskettes. If the installation source is a CD-ROM or network drive, *<source_volume>* and *<source_description>* are ignored (although these fields must be present in the command).

Example

```
CopyDriverToServer SYSTEM, '*.LAN', 'NETWARE-3', "NetWare  
diskette [3]"
```

The *.LAN files are copied to the SYS:SYSTEM directory.

CopyDriverToStartup

Syntax

```
CopyDriverToStartup <file_spec>, <source_volume>,  
<source_description>
```

Description

CopyDriverToStartup replaces driver files in the startup or boot directory (where STARTUP.NCF is) with new driver files. The source files are assumed to be those on the distribution CD (which might have been copied to a user-specified directory). <file_spec> names the files to be copied, and can be *.LAN, *.DSK, <directory>/*.LAN or <directory>/*.DSK. <source_volume> specifies the name of a diskette volume label and <source_description> specifies the string used to prompt for the diskette. If the installation source is a CD or network drive, <source_volume> and <source_description> will be ignored (although these fields must be present in the command).

Example

```
CopyDriverToStartup '*.LAN', 'NETWARE-3', "NetWare  
diskette [3]"
```

The *.LAN files are copied to the user-designated DOS startup directory where the server boot files reside.

CopyToServer

Syntax

```
CopyToServer <target_directory_path>, <file_spec>,  
<source_volume>, <source_description>
```

Description

CopyToServer specifies a file (or a group of files using wildcards) to copy to the system volume of the server.

<target_directory_path> is a directory path relative to SYS: where the files will be copied. *<file_spec>* names the files to be copied; it might be in the “directory/file” form to copy files from a subdirectory. *<source_volume>* specifies the name of a diskette volume label and *<source_description>* specifies the string used to prompt for the diskettes. If the installation source is a CD-ROM or network drive, the *<source_volume>* and *<source_description>* fields are ignored (although these fields must be present in the command).

Example

```
CopyToServer 'SYSTEM', '*.*', 'SYSTEM-2', "NetWare  
diskette [4]"
```

Files matching the DOS file specification (including DOS wildcard names) are copied from the volume SYSTEM-2 (or from a user-specified hard disk or network directory) to directory SYS:SYSTEM. If the volume SYSTEM-2 is not present, the user will be prompted to insert the NetWare CD.

CopyToStartup

Syntax

```
CopyToStartup <file_spec>, <source_volume>,  
<source_description>
```

Description

CopyToStartup copies files to the startup or boot directory (where STARTUP.NCF is). The source files are assumed to be those on the distribution diskettes (which might have been copied to a user-specified directory).

<file_spec> names the files to be copied. To copy files from a subdirectory, *<file_spec>* can be of the form “directory/file”. *<source_volume>* specifies the name of a diskette volume label and *<source_description>* specifies the string used to prompt for the diskettes. If the installation source is a CD or network drive, *<source_volume>* and *<source_description>* are ignored (although these fields must be present in the command).

Example

```
CopyToStartup 'SERVER.EXE', 'SYSTEM-3', "NetWare diskette  
[3]"
```

SERVER.EXE is copied to the user-designated DOS startup directory where the server boot files will reside.

Exec

Syntax

Exec *<filename>*

Description

Exec issues the operating system command LOAD *<filename>*, pauses until the child NLM unloads, then continues executing. To load from other subdirectories of the system volume besides \SYSTEM, specify a filename (SYS:*<directory>*/*<file>* and *<directory>*/*<file>*).

Example

Exec MY.NLM

MY.NLM will be loaded and executed. Exec will follow the normal NLM search path to find MY.NLM. Control will return to the installation after Exec exits and unloads.

ProductRecord

Syntax

ProductRecord *<product ID (string)>*, *<record type>*, *<record data>*

Description

ProductRecord creates a record in the product database with the ID string *<product ID>* and the record type and data indicated.

Record Type	Data
0	Version string (10 char max)
1	Product description (60 char max)
[2]	Configuration NLM command line(255 char max)
[3]	Configuration text file specification (255 char max)
[4]	Un-install NLM command line (255 char max)
[5]	Delete AUTOEXEC line (255 char max)

Record Type	Data
[6]	Delete STARTUP line (255 char max)
[7]	Delete file line (255 char max)

Example

ProductRecord MYPROD, 1, "Description for my product"

This creates a product description record for MYPROD with the quoted description.

RegisterLanguage

Syntax

RegisterLanguage *<language ID>*, *<language name>*

Description

RegisterLanguage renames *<language ID>* to the respective name *<language name>*. This exists typically to allow non-standard languages to be registered when they are installed.

Example

RegisterLanguage 17, TURKISH

This command aliases TURKISH to ID 17.

SaveLanguageFile

Syntax

SaveLanguageFile *<file>*

Description

SaveLanguageFile copies *<file>* in the DOS startup directory to the directory indicated by the old language ID *<startup directory>/<old language ID>*. This might involve creating a new directory. If the directory path for the new file does not exist, it will be created.

Example

SaveLanguageFile SERVER.MSG

If the current language ID is 4, SERVER.MSG in the DOS startup directory (BOOT directory) is copied to the subdirectory 4 in the DOS startup directory.

Spawn

Syntax

Spawn <file name>

Description

Spawn issues the operating system command LOAD <file_name>, then the installation continues to execute. See “[Exec](#)” on page 123.

Example

Spawn MY.NLM

The MY.NLM file is loaded and executed. Spawn follows the normal NLM search path to find MY.NLM. The installation and the child NLM both execute, sharing the CPU through context switches.

External Commands

This section describes commands provided by ICMD.NLM, a companion to the NetWare Installation NLMs (INSTALL.NLM and NWCONFIG.NLM). See “[NetWare Installation Command Version Availability](#)” on page 161 for a table showing the ICMD versions that support these commands.

Version 2.10 External Command Compatibility

If you intend to use ICMD.NLM 2.18 or greater, do not copy this new version to SYS:SYSTEM. Instead, copy it to a different directory and load it from there.

For example, the script commands below will copy ICMD.NLM to a temporary directory and load from there.

```
CopyToServer SYSTEM\TMP, ICMD.NLM, "", ""  
Command TMP\ICMD
```

Using this method ensures that the ICMD.NLM version in SYS:SYSTEM is the actual 4.10 version and that all built-in products that use it will work properly. The new ICMD.NLM might still be fully backward-compatible, but it has not yet been fully tested in that regard.

External Command Syntax

To use any of the external commands made available by the ICMD.NLM command handler, include the statement command [*<filepath>*] ICMD in the script file. Use CopyToServer to copy ICMD.NLM to a temporary directory (for example, SYS:SYSTEM\TEMP), then use command to run it from there (for example, command SYS:SYSTEM\TEMP\ICMD). This removes any compatibility problems associated with using the standard ICMD.NLM in SYS:SYSTEM. You can create then add additional commands to your own version of ICMD.NLM (after you rename the file) to perform application-specific functions.

Commands

Activate

Syntax

Activate

Description

Activate causes the installation screen to be activated.

Example

Activate

The installation screen will be displayed for further script processing.

AppendFile

Syntax

AppendFile *<src var name>*, *<src file spec>*, *<src vol name>*,
<src descr>, *<dest var name>*, *<dest dir>*, *<dest vol name>*,
<dest descr>

Description

AppendFile appends the contents of the source file onto the destination file. It creates a temporary file that is as large as the destination file, then renames that file to the destination file. Wildcard characters for *<src file spec>* are not allowed.

Example

```
AppendFile input, file1, 'NETWARE-1', "NW [1]", output,  
file2, '', ''
```

The user is prompted for diskette NW [1], which is verified by checking for volume label NETWARE-1. The FILE1 on that diskette is appended to FILE2 in the directory corresponding to output.

AppendTextToFile

Syntax

```
AppendTextToFile <src var name>, <src file spec>, <src vol  
name>, <src descr>, <text>
```

Description

AppendTextToFile appends the contents of the literal text onto the destination file. It also places a date timestamp with every entry. Wildcard characters for *<src file spec>* are not allowed.

If the file is found, the value of variable NWSTATUS will be zero; otherwise it will be non-zero.

Example

```
AppendTextToFile input, file1, 'NETWARE-1', "NW[1]",  
'Installation Complete'
```

The user is prompted for disk NW[1], which is verified by checking for volume label NETWARE-1. The FILE1 on that disk will be appended to FILE2 in the directory corresponding to the output.

CheckFile

Syntax

CheckFile <var name>, <file spec>, <vol name>, <description>

Description

CheckFile checks for the existence of <file spec> at a path determined by the value of <var name>. If the path is a floppy, and <vol name> is non-null (not ""), the user will be prompted for disk <description> if it is not already in the drive.

If the file is found, the value of variable NWSTATUS will be zero; otherwise it will be non-zero.

Example

```
CheckFile NWSRC, file1.dat, '', ''
GotoIfNEqual '%{NWSTATUS}', 0, FileNotFound
File found
.
.
Label FileNotFound
```

In this example, a check is made for a file (FILE1.DAT). If the file is found at the path determined by NWSRC, execution continues on the next line. If the file is not found, control branches to label FileNotFound.

Config

Syntax

Config <flag>

Description

Config creates a configuration file with available default information from the installation. If <flag> is 1, AUTOEXEC.NCF is created on SYS:SYSTEM; if 0, STARTUP.NCF is created in the server boot path.

Example

Config 1

This command creates AUTOEXEC.NCF, with server name, internal net address, configured LAN driver load and bind commands, directory service

and time services information. The existing AUTOEXEC.NCF on SYS:SYSTEM is overwritten.

Console

Syntax

Console *<text>*, *<delay in seconds>*

Description

Console enters the text on the system console screen and delays *<delay in seconds>* before returning control back to the calling process. Because the system installation process executes in a different thread from the console, it is possible that the next command might finish before this Console command does. If the delay is set at -1, *Console* will delay until the system console screen has processed all the commands in its buffer.

Example

```
Console 'load ne2000 frame=ethernet_802.3 int=3 port=300',  
10
```

```
Console 'bind ipx to ne2000 net=1240000', 3
```

These commands load and bind an NE2000™ driver to IPX™.

CopyFile

Syntax

CopyFile *<recurse flag>*, *<directory flag>*, *<empty flag>*,
<attribute flag>, *<attributes>*, *<src var name>*, *<src file
spec>*, *<src vol name>*, *<src descr>*, *<dest var name>*, *<dest
dir>*, *<dest vol name>*, *<dest descr>*, [*<conditional copy flag>*]

Description

CopyFile copies files (wildcards are allowed in *<src file spec>*) from the source path to the destination path.

<recurse flag> (0|1)

Value	Description
0	Do not copy subdirectories recursively.
1	Copy subdirectories recursively.

<directory flag> (0|1|2|3)

Value	Description
0	Source is a file.
1	Source (including <i><src file spec></i>) is a directory; copy directory contents to destination.
2	Source and the destination are files (file-to-file copy). <i><recurse flag></i> must be 0 if <i><directory flag></i> is 2
3	Source (including <i><src file spec></i>) is a directory; copy directory contents to destination only if that directory already exists on the destination.

<empty flag> (0|1)

Value	Description
0	No error if no files are found.
1	Error if no files are found.

<attribute flag> (0|1|2)

Value	Description
0	Use the default file set attributes.
1	Use the source file's attributes.
2	Use the attribute specified by <i><attributes></i> (must be used to copy to DOS drive).

<attributes>

For a DOS file:

Attribute	Meaning
00000001	Read Only
00000002	Hidden
00000004	System
00000008	Volume Label

For a NetWare file:

Attribute	Meaning
00000001	Read Only
00000002	Hidden
00000004	System
00000008	Execute
00000010	Subdirectory
00000020	Archive
00000080	Shareable
00000700	Smode
00001000	Transaction
00004000	Read Audit
00008000	Write Audit
00010000	Immediate Purge
00020000	Rename Inhibit
00040000	Delete Inhibit
00080000	Copy Inhibit

Reserved path names (<src|dest var name>) are NWSRC, NWDST and NWBOOT, the standard source, destination and boot path for NetWare files. <dest dir name> can be a null string.

<conditional copy flag>

Value	Description
0 (or not present)	Unconditionally copy this file.
1	Copy if destination file is not present.
2	Copy if destination file is not present; if it is, prompt user (no version check).
3	Copy if destination file is not present or if the source file version is newer than the destination file version.
4	Copy if destination file is not present or if the source file version is newer than the destination file version; otherwise, prompt the user.
5	Copy if destination file is present (no version check).
6	Copy if destination file is present and source file version is newer than destination file version.
7	Copy if destination file is present and source file version is newer than destination file version; otherwise, prompt the user.
8	Copy if destination file is not present or if source file version is newer than destination file version (refresh with new files).
9	Copy only if destination file is present and source file version is newer than destination file version (refresh existing files).

Example

```
CopyFile 0, 0, 1, 0, 0, input, *.* , 'NETWARE-1', "NW [1]",
output, '', '', ''
```

This is a continuation of the examples for “[GetPath](#)” on page 141. The user is prompted for diskette NW [1], and the diskette is verified by checking for volume label NETWARE-1. All files on the diskette are copied to the subdirectory the user indicated for output.

CopyFloppyImage

Syntax

CopyFloppyImage *<floppy type flag>*, *<diskette name>*, *<src var name>*, *<src file spec>*, *<src vol name>*, *<src descr>*, *<dest var name>*, *<dest dir>*, *<dest vol name>*, *<dest descr>*

Description

CopyFloppyImage copies a diskette image file sector by sector to the specified drive (destination path which must be a diskette drive).

Variable	Description
<i><floppy type flag></i> (0 1)	0 indicates a 3.5-inch high-density drive. 1 indicates a 5.25-inch high-density drive.
<i><diskette name></i>	The external label for the diskette.

Example

```
GetPath, dst, 2, 'A:', ''
CopyFloppyImage 0, "Disk 1", 3.5\WSDOS_1.IMG, '', '', dst,
'', '', ''
```

The floppy image specified by the source path is copied to the diskette in the specified drive.

Delay

Syntax

Delay *<delay in seconds>*

Description

Delay relinquishes control for *<delay in seconds>* seconds before returning control back to the calling process. If a negative value is used, the delay is a random value from 0 to the absolute value of *<delay in seconds>*.

Example

```
Delay '-10'
```

This delays randomly from 0 to 10 seconds.

DiskReset

Syntax

DiskReset *<var name>*

Description

DiskReset tells DOS to rescan the directories on the *<var name>* floppy drive. This is necessary because the drive change interrupt is disabled while NetWare has control.

Example

Assuming myDir corresponds with A:\

DiskReset myDir

Drive A:\will be rescanned.

Dismounted CD

Syntax

DisMountCD *<CD Volume Name>*

Description

DisMountCD is to be used with PromptForCD (below). It is used to dismount a CD volume that has been mounted via the PromptForCD command.

Example

DisMountCD 'CDVolumeName'

Display_Text_File

Syntax

Display_Text_File *<Path>*, *<Filename>*, *<Completion Code>*

Description

Display_Text_File displays an ASCII text file. The user can scroll the text in any direction to read the entire contents of the file. Scroll bars automatically display if needed. The maximum file size is 30 KB for the file.

Example

```
GetPath sys, 1, 'SYS:', ''
```

```
Display_Text_File sys, "license.txt", ccode
```

The completion code will return a 0 (zero) for a successful return. Anything else is an error.

Display

Syntax

```
Display <0|1|2>, "...<text>..."
```

Description

Display displays a message, accompanied by a beep if the first argument is 1. If the argument is 2, the message is displayed as a copy status.

Example

```
Display 0, "Product XYZ installation is complete."
```

The text is displayed (without a beep), and the user can press Enter to continue.

DSInst

Syntax

```
DSInst <time zone name>, <time server type>, <daylight  
flag>, <daylight start>, <daylight end>, <daylight  
offset in seconds>, <tree name>, <tree address>,  
<container object name>, <admin name>, <admin password>,  
<replica flag>, <upgrade bindery flag>, <root server  
flag>
```

Description

DSInst installs the directory with default time synchronization.

Variable	Description
<time zone name>	Time zone name (works as a system SET parameter)
<time server type>	Time server type (works as a system SET parameter): single, reference, primary, secondary

Variable	Description
<daylight flag>	1: Daylight savings time exists in this time zone 0: Daylight savings time doesn't exist in this time zone
<daylight start>	"set parameter" daylight savings time start string. For Example First Sunday of April at 2:00:00 a.m
<daylight end>	"set parameter" daylight savings time end string. For Example Last Sunday of October at 2:00:00 a.m.
<daylight offset in seconds>	Typically this is 3600 (seconds per hour), or zero if daylight saving time is not applicable.
<tree name>	DS tree name
<tree address>	Internal IPX address of the SAP server for the tree
<container object name>	Full DN of container
<admin name>	Full DN of Admin object (must have supervisor rights on the container)
<admin password>	Password for <admin name>
<replica flag>	1: Install a replica on this server; 0: don't install
<upgrade bindery flag>	1: Upgrade the bindery if it exists; 0: don't install
<root server flag>	1: Make this a new tree; 0: don't make this a new tree

Example

```
DSInstMST7MDT, SECONDARY, 1, '(APRIL SUNDAY FIRST 2:00:00 AM)', '(OCTOBER SUNDAY LAST 2:00:00 AM)', 3600, URSA, FACE3234, 'O=Novell', 'CN=Admin.O=Novell', '', 1, 1, 0
```

Time services will be installed with this server as a secondary server using existing tree name URSA. Directory services will be installed, with this server in container O=Novell. This server will have a replica installed, and its bindery will be upgraded.

EraseFile

Syntax

EraseFile <directory flag>, <var name>, <file spec>, <vol name>, <vol descr>

Description

EraseFile recursively erases the file or directories indicated in <file spec>. Wildcards are acceptable. In NetWare, files can be removed no matter what their attributes; in DOS, only normal files can be removed.

IMPORTANT: Use this command with care to delete only the intended data.

If <directory flag> is 1, <file spec> must be a directory name; the contents of the directory will be deleted, but the directory will not.

Example

If myDir corresponds to VOL1:\.

EraseFile 1, myDir, '', '', ''

The contents of directory VOL1:\ will be erased.

EditNCF

Syntax

EditNCF <ncf path var>, <ncf file name>, <backup ext>, <ccode>

Description

EditNCF edits the specified NCF file as follows:

- ♦ Writes any lines in the EditNCF_ADDLINE list at the beginning of the NCF file.
- ♦ Deletes any lines that match lines in the addline list.
- ♦ Comments out any lines containing keystings in the EditNCF_KEYSTRINGS list.
- ♦ Any other lines are copied unchanged.

Example

```
GetPath startup, 1, 'C:\\NWSERVER', ''
EditNCF_KEYSTRING ''
EditNCF_KEYSTRING 'PK411.NLM'
EditNCF startup, 'startup.ncf', 'bak', ccode
```

The contents of C:\\NWSERVER\\STARTUP.NCF will be searched for a line containing PK411.NLM and will be commented out by the EditNCF command. Ccode will contain the following:

- 0 - Success
- 1 - Duplicate Extension
- 2 - Open Error
- 3 - Read Error
- 4 - Write Error
- 5 - NCF to Backup Extension Error
- 6 - Tmp to NCF Error

EditNCF_ADDLINE

Syntax

```
EditNCF_ADDLINE <LineToBeAdded>
```

Description

EditNCF_ADDLINE adds a line of text to the list of lines to be added at the top of the file being edited with EditNCF.

Example

```
EditNCF_ADDLINE ''
EditNCF_ADDLINE 'LOAD PK411.NLM'
EditNCF startup, 'startup.ncf', 'bak', ccode
```

The first line will clear the ADDLINE list. The second line will add the string “LOAD PK411.NLM” to the top of the STARTUP.NCF file.

EditNCF_KEYSTRINGS

Syntax

EditNCF_KEYSTRINGS <keystring>

Description

EditNCF_KEYSTRINGS defines a list of keystings to be used by EditNCF when determining which lines to comment out. (A line will be commented out if it contains any of the keystings).

NOTE: The list must be terminated with a null string (empty quotes) for the last entry. This command can be used multiple times. Each time replaces the previously defined list.

Example

```
EditNCF_KEYSTRINGS ''  
EditNCF_KEYSTRINGS 'PK411.NLM', 'ADTRSTFX', 'AUTODUMP',  
    'CLSSCRFX', 'EAPURGFX', 'EVNTRPFX', 'GETDIRFX', ''  
EditNCF startup, 'startup.ncf', 'bak', ccode
```

The first line clears the KEYSTRING list. The second line adds the strings to the list to be commented out of the STARTUP.NCF file.

ExtractVersionNumbers

Syntax

ExtractVersionNumbers <version string>, <major var name>,
<minor var name>, <revision var name>

Description

ExtractVersionNumbers parses a version string and returns the major version number, minor version number, and revision number as integers. Version string is parsed and leading non-digits are ignored. The variables are filled with the major, minor, and revision values for the version string. If no revision value is in the version string, a zero is returned. If the revision value is a non-digit value, a numeric revision value is returned (i.e., A = 1, B = 2, etc.).

Example

```
SetVar version, "v2.11"  
ExtractVersionNumbers version, major, minor, revision
```

The variable version contain the string “v2.11”. ExtractVersionNumbers returns a value of 2 in the variable major, a value of 11 in the variable minor. And a value of 0 in the variable revision.

FileVersion

Syntax

```
FileVersion <src var name>, <src file spec>, <src vol name>,  
<src descr>, <Module major number>, <Module minor number>,  
<Module rev number>, <Module description>, <return code>
```

Description

FileVersion returns the major, minor, and revision numbers as well as the description string of the NetWare Loadable Module (NLM, HAM, CDM, LAN, etc.) as long as the return code is 0.

IMPORTANT: This works only for NetWare Loadable Modules (that is, it does not work with .EXE or .DLL files, etc.).

Example

```
GetPath1, 1, 'SYS:\\SYSTEM'  
File Version path1, 'DS.NLM', '', '', DSMajor, DSMajor,  
DSRev, DSDesc, DSCode
```

GetDOSServer

Syntax

```
GetDOSServer <var name>
```

Description

GetDOSServer returns the default DOS server number in <var name> on SFT* III servers.

Example

```
GetDOSServer DOSServer
```

The value of the variable DOSServer will be either 0 or 1. If the value is anything else, the server is not running SFT III.

Syntax

GetPath <var name>, <path type>, <default>, <prompt>, [<base var name>]

Description

GetPath prompts the user for a path using the prompt. The prompt string will be displayed, with “%s” (like C-language print formatting) being replaced by the <default> string.

The keystrokes to modify will be added to your prompt. Trailing backslashes are always removed before the path is displayed. <var name> is a variable name that can be used later in a CopyFile command. If <prompt> is a null string, the user is not prompted; the path variable is set. If <base var name> exists, it will be used as a basis for the new variable (the remote connection number will be maintained, etc.).

<path type>

Value	Description
1	Allow any path.
2	Allow floppy only (including remote).
3	Allow DOS only (including remote).
4	Allow NetWare local path only.
5	Allow local floppy only.

Example

GetPath input, 1, 'A:', "Files will be copied from %s\\."

The user will see the following prompts:

Files will be copied from A:\

Press <F3> to specify a different path.

Press <F4> to specify a remote path.

Press <Enter> to continue.

Goto

Syntax

`Goto <label_name>`

Description

Goto causes execution to continue at the first occurrence of label `<label_name>`.

The scope of a label is always local to a file set. Therefore, a Goto statement cannot transfer execution to a file set different from the current one.

Example

```
Goto Done  
Label Done
```

The statement `Goto Done` will cause execution to continue at the label `Done`.

GotoIfEqual

Syntax

`GotoIfEqual <larg1>, <arg2>, <label_name>`

Description

GotoIfEqual causes execution to continue at the first occurrence of Label `<label_name>` if `<arg1>` is equal in value to `<arg2>`. Both `<arg1>` and `<arg2>` must be integers.

The scope of a label is always local to a file set. Therefore, a Goto statement cannot transfer execution to a file set different than the current one.

Example

```
GotoIfEqual 0, 1, Error  
Goto Done  
Label Error
```

Since 0 is not equal to 1, execution will not continue at label `Error`.

NOTE: GotoIfEqual performs an integer comparison, not a string comparison.

GotoIfNEqual
GotoIfGreater
GotoIfLess
GotoIfGrEqual
GotoIfLsEqual

Syntax

```
GotoIfNEqual <arg1>, <arg2>, <label_name>  
GotoIfGreater <arg1>, <arg2>, <label_name>  
GotoIfLess <arg1>, <arg2>, <label_name>  
GotoIfGrEqual <arg1>, <arg2>, <label_name>  
GotoIfLsEqual <arg1>, <arg2>, <label_name>
```

Description

These are identical to **GotoIfEqual** (page 142), except that execution branches only if (respectively):

```
<arg1> not equal to <arg2>  
<arg1> is greater than <arg2>  
<arg1> is less than <arg2>  
<arg1> is greater than or equal to <arg2>  
<arg1> is less than or equal to <arg2>
```

The scope of a label is always local to a file set. Therefore, a Goto statement cannot transfer execution to a file set different from the current one.

NOTE: GotoIf* performs an integer comparison, not a string comparison.

Is_NLM_Active

Syntax

```
Is_NLM_Active <NLM Name>, <Completion Code>
```

Description

Is_NLM_Active searches the loaded modules list and returns 1 if the NLM is loaded, or 0 if the NLM is not present in memory.

Example

```
Is_NLM_Active "Monitor.nlm", ccode
```

IsSubString

Syntax

IsSubString <string>, <substring>, <index>

Description

IsSubString returns the zero based <index> of <string> where <substring> starts, if <substring> is indeed contained within <string>, otherwise <index> is -1.

Example

```
IsSubString 'Little Miss Muffet sat on', 'Miss Muffet',  
index
```

In this example, <index> would return as 7.

Label

Syntax

Label <label_name>

Description

Label serves only as a target of a goto statement with <label_name>.

IMPORTANT: The scope of a label is always local to a file set. Therefore, a Goto statement cannot transfer execution to a file set different from the current one.

Example

```
Goto Done  
Label Done
```

The Goto Done statement will cause execution to continue at Label Done.

LangVar

Syntax

LangVar <default>, <lang var>, <src var dir name>, <src vol name>, <src descr>

Description

LangVar sets a variable to the number of a language. It starts with *<src var dir name>*, then it looks for a subdirectory whose name is a number that matches the current server language number. If the subdirectory is found, *<lang var>* is set to that number; otherwise, *<lang var>* is set to *<default>*.

Example

Assuming the current language is 6:

```
LangVar 4, lang, NWSRC, '', ''
```

This command looks in the source install directory for a subdirectory named 6. Finding it, it sets lang to 6.

Menu

Syntax

Menu *<var name>*, *<Prompt>*, *<# of menu options>*, *<default menu option>*, *<first choice>*, *<first value>*, *<second option>*, *<second value>* [*<third option>*, *<third value>*,] [*<fourth option>*, *<fourth value>*]

Description

Menu command will display a window with the *<Prompt>* showing in a header area. The *<choices>* will display in a scrolling area below the header. The *<# of menu options>* is 1 based. The *<default menu option>* is zero based. The entire command is terminated without a comma after the final value.

Example

Menu done, "Are you ready to continue?", 2, 0,

"Yes", 1,

"No", 0

The Menu command displays a box on the screen with the Prompt "Are you ready to continue?" Below it the choices are "Yes" and "No." The "Yes" option is highlighted as the default option. Upon selecting the option, the value will be placed in the variable. The values must be integers.

Syntax

NLMExec *<block flag>*, *<command line>*

Description

NLMExec executes the NLM specified by *<command line>*. If *<block flag>* is 1, NLMExec waits for the NLM to complete execution, then continues. NLMExec is the external command version of the [Exec \(page 123\)](#) command. NLMExecIO is identical to NLMExec except it executes the command line on the default DOS server on a NetWare SFT III server. See [“SetDOSServer” on page 149](#) for more information.

Example

NLMExec 1, PINSTALL

This command executes PINSTALL.NLM and waits for it to finish.

Partitions

Syntax

Partitions *<delete flag>*

Description

Partitions creates NetWare partitions as needed on all available devices. If *<delete flag>* is 1, all existing non bootable partitions will be deleted. If *<delete flag>* is 0, they will be left intact. The minimum allowable partition size is 1 MB, according to default rules (see [“@DeletePartition” on page 105](#)).

Example

For one existing device with a DOS (active) partition and a NetWare 286 partition:

Partitions 1

This deletes the 286 partition and creates a NetWare partition in the remaining space.

PromptForCD

Syntax

PromptForCD *<CD Volume Name>*, *<seconds to mount>*

Description

PromptForCD is to be used with DisMountCD (above). PromptForCD will prompt the user to insert the CD labeled *<CD Volume Name>* into the CD drive and then will attempt to mount the CD volume within the *<seconds to mount>* time frame.

Example

PromptForCD 'CD 1', 30

Quit

Syntax

Quit

Description

Quit will exit the script processing at this point. No further processing will take place.

Example

GotoIfEqual %{variable1}, %{true}, Continue_On
Quit

Label Continue_On

ReadProductRecord

Syntax

ReadProductRecord *<productID>*, *<recordtype>*,
<recorddatavarname>, *<ccode>*

Description

ReadProductRecord reads the record in the products database matching the *<productID>* and *<recordtype>* specified and returns the corresponding data.

This command is the counterpart to the ProductRecord command. See [“ProductRecord” on page 123](#) for more information on record types.

Example

ReadProductRecord MYPROD, 0, version, ccode

The command will search the products database and return the value for *<version>* for product 'MYPROD'.

Read_Var_File

Syntax

Read_Var_File *<path>*, *<filename>*, *<completion code>*

Description

Read_Var_File will read the contents of the filename and create variables for script processing. The file is an ASCII formatted file with the content as follows:

“Variable1=true”

“Variable2=false”

“Variable3=Servername”

Example

Read_Var_File “sys:system”, “varfile.txt”, ccode

NOTE: Ccode will return the file open status. 0 is success, anything else is an error. If the variable to the left contains any spaces, leading or trailing, the spaces will become part of the variable name and must be included with the variable when referencing it.

SetDir

Syntax

SetDir *<var name>*, *<relative dir>*, *<vol name>*, *<vol descr>*, *<attributes>*, *<0|1>*, *<rights>*

Description

SetDir creates directories (if they do not already exist), according to the *<var name>* obtained from [GetPath \(page 141\)](#). The *<relative dir>* value can be null. *<attributes>* are the attributes to use when creating the directory; 0

indicates normal attributes. If the *<0|1>* argument is 1, the server container object (or everyone) is given *<rights>* rights to the directory.

Example

If myDir corresponds to VOL1:\

```
SetDir myDir, DOC, '', '', 10, 1, 0
```

The directory VOL1:\DOC will be created and all applicable users will have rights to it.

SetDOSServer

Syntax

```
SetDOSServer <engine number>, <cocode>
```

Description

SetDOSServer specifies the *<engine number>* to be made the default DOS server (valid numbers are 0 and 1). This will set the default server used by the OS APIs.

NOTE: *DiskReset* and *GetPath* can be directed to a particular IOEngine by first setting the DOS server as needed. This allows you to essentially map a path variable to a particular IOEngine. From that point on, that path variable will be associated with that IOEngine regardless of what the default DOS server is set to. Therefore, any commands that use path variables will target the IOEngine associated with the path variable rather than the default.

Example

```
SetVar IOEngineNumber, 0
```

```
SetDOSServer IOEngineNumber, ccode
```

The server's default IOEngine 0 will now be the default DOS server. Ccode will have a 0 for its value on success and a -1 for a failure.

SetLConfigLang

Syntax

SetLConfigLang *<value>*

Description

SetLConfigLang looks for the LCONFIG.SYS file in the server boot directory. The default server language ID number is changed to *<value>*.

Example

SetLConfigLang 9

The default server language ID number in the LCONFIG.SYS file is changed to 9 (Japanese).

SetVar

Syntax

SetVar *<variable name>*, *<variable value>*, [*<Prompt>*]

Description

SetVar sets a variable with *<variable name>* to the *<variable value>* string value. If the value does not exist, one is created. The variable value cannot exceed 127 characters in length.

Example

SetVar message, "Hello World!"

This causes a variable to be created with name "message," and its value set to the string "Hello World!"

NOTE: The Prompt option is only available in version 3.25+.

SGotoIfEqual
SGotoIfNEqual
SGotoIfGreater
SGotoIfLess
SGotoIfGrEqual
SGotoIfLsEqual

The SGotoIf commands have the same options as the GotoIf commands. The SGotoIf commands perform a string comparison instead of an integer comparison.

SpaceCheck

Syntax

SpaceCheck *<path var name>*, *<value>*

Description

SpaceCheck looks at *<path var name>*. If it matches a NetWare volume, SpaceCheck checks whether the volume is large enough for *<value>* bytes, and whether the volume has enough free space for *<value>* bytes. If the volume is not large enough, the installation aborts. If there is not enough free space, the user is alerted and allowed to continue.

Example

Assuming srcVar corresponds to VOL1:\FILES

SpaceCheck srcVar, 1000000

Volume VOL1: will be checked for one million bytes of free space.

NOTE: ICMD.NLM versions 3.25 and older do not support SpaceCheck on DOS drives. Newer versions support this drive option.

SrchNCF

Syntax

SrchNCF *<ncf path var>*, *<ncf file name>*, *<keystring>*,
<foundline var name>

Description

SrchNCF searches an .NCF file for line containing a substring matching *<keystring>* (non case-sensitive). If found, the line of text will be returned; otherwise *<foundline var name>* will be empty.

NOTE: The same value as not found will be returned if an error is encountered (for example, invalid filename, read error, etc). It is assumed that this command will be used before calling [EditNCF \(page 137\)](#) which returns a more detailed completion code that can be acted on as necessary.

Example

```
GetPath sys, 1, 'SYS:\\', ''
```

```
SrchNCF sys, 'SYSTEM\\AUTOEXEC.NCF', "Load Monitor", ccode
```

The SrchNCF command will search the SYS:\SYSTEM\AUTOEXEC.NCF file for the string 'Load Monitor' and return the line number in ccode if found.

ValueSet ValueAdd

Syntax

ValueSet *<var name>*, *<value>*
Value Add *<var name>*, *<value>*

Description

ValueSet sets, and ValueAdd adds to, the numeric contents of variable *<var name>*.

Example

```
ValueSet srcVar, 1
```

The variable srcVar is created if it did not exist and is set to 1.

Volumes

Syntax

Volumes *<minimum vol SYS: size in sectors>*

Description

Volumes creates and mounts volumes on this server, with the volume SYS: placed on the first device larger than *<minimum volume SYS: size in sectors>* (512 bytes per sector). Additional volumes, named “VOL1”, “VOL2”, etc., will be created on other devices, one per device.

Example

For one existing device with 50 MB and a NetWare partition, but no volumes:

Volumes 51200; 25 MB minimum

This command creates volume SYS: on the device and mounts it. For more information on creating and mounting NetWare volumes, see the Volume Management API.

Write_Var_File

Syntax

Write_Var_File *<path>*, *<filename>*, *<varname>*, *<var value>*, *<completion code>*

Description

Write_Var_File will write the varname and var value to the filename specified by the path/filename. The file is an ASCII formatted file with contents as follows:

“Variable1=true”

“Variable2=false”

“Variable3=Servername”

Example

Write_Var_File “sys:system”, “varfile.txt”, “Variable1”, “true”, ccode

NOTE: Ccode will return the file open status. 0 is success, anything else is an error. If the variable to the left contains any spaces, leading or trailing, they will be

part of the variable name and must be included with the variable when referencing it later. If the filename doesn't exist, it will be created. The varname and var value will then be written. If the file does exist, the varname and var value will be appended to the contents of the file.

External Command Programming Interface

The external command programming interface contains the functions described below.

IMPORTANT: These functions require ICMD.NLM 2.18 or later.

ICMDSetVar

Use the ICMDSetVar function to set a script variable programmatically.

Function

int ICMDSetVar (char **variableName*, char **variableValue*)

**variableName*: Pointer to name of variable to set

**variableValue*: Pointer to string representing value of variable being set

Return

0 if successful; non-zero error code if unsuccessful.

Description

ICMDSetVar is a function exported by ICMD.NLM that another NLM can call (for instance, in a blocking NLMExec command). This lets the NLM set a variable within a script being executed by ICMD.NLM so the NLM can communicate with the script, changing the control flow, etc.

Example

If MYNLM.NLM has code as follows:

```
ICMDSetVar("mynlmvar", "hello world"); exit();
```

and the script looks like this:

```
NLMExec 1, mynlm  
Display 0, "Information: %{mynlmvar}"
```

then this popup text box would be displayed:

Information: hello world

ICMDGetVar

Use the ICMDGetVar function to get the value of a script variable.

Function

```
int ICMDGetVar (char *variableName, char *variableValue)
```

**variableName*: Pointer to name of variable

**variableValue*: Buffer containing value of variable; must be at least 128 bytes

Return

0 if successful; non-zero error code if unsuccessful or if variableName does not exist.

Description

ICMDGetVar is a function exported by ICMD.NLM that another NLM can call. This lets the NLM set a variable within a script being executed by ICMD.NLM so the NLM can communicate with the script, changing the control flow, etc.

Example

If a script looks like this:

```
SetVar myvar, "Hello"  
NLMExec 1, mynlm
```

and if MYNLM.NLM has code as follows:

```
char buffer[128];  
ICMDGetVar("myvar", buffer);
```

then the value in buffer would be the null-terminated string:

"Hello".

External Command Variable Substitution

A variable, such as the value returned by [GetPath \(page 141\)](#), can be used inside any quoted string within an executed external command. The variable is global. It goes out of scope only when the command processor is replaced by a different one. The variable can be dereferenced explicitly by an expression `%{<var name>}` within another string.

Variable	Description
NWSERVER	The name of the server the script is processing on.
NWSRC	Source path where script is found.
NWDST	Destination path (where server will boot from).
NWBOOT	Current path (where server was booted from).
NWLANG	Language number (4 = English, etc.).
COUNTRY	Country ID (DOS country specifier).
CODEPAGE	Codepage number (DOS code page specifier).
OSTYPE	NetWare operating system type: 0 - Native 1 - OS/2 2 - SFT III
LOADERTYPE	Type of loader used to start NetWare: 1 - DOS 2 - OS/2 3 - Windows 3.1
SERVCONFIGTYPE	NetWare server configuration: 0 - Native 1 - SFT III I/O Engine 2 - SFT III MS Engine
SFTLEVEL	Level of active System Fault Tolerance for NetWare.
OSMAJORVERSION	The major version number for the NetWare OS.
OSMINORVERSION	The minor version number for the NetWare OS.
OSREVISION	The revision level for the NetWare OS.

All path variables, including the predefined ones, allow subfield specifiers in the form *<path var>.<specifier>*.

<i><path var></i>	<i><specifier></i>
PATH	String containing the actual path.
VOL	Disk volume name.
PROMPT	Disk volume prompt.
TYPE	Path type.
SUBTYPE	Path subtype.
CONN	Connection number (hex).
ENGINE	Engine number.
TYPE	Values: 1 local server 2 remote server 3 local DOS 4 remote DOS (via RCONSOLE)
SUBTYPE	Values: 0 unknown 1 floppy 2 cd 3 network 4 other

Example

```
NLMExec 1, 'Pinstall %{NWLANG} %{NWSRC.CONN}'
```

If the server language is English, and the connection number for NWRSC is 5, it is as if the following were typed on the system console:

```
'load PINSTALL.NLM 4 5'
```

Installation NLM Command Line Options

Command line options can be preceded by '-', but this is not required.

IMPORTANT: These options are not intended for general distribution; they apply only to the NetWare installation NLM. **Other Switches** are not guaranteed to be supported in all versions.

User-Documented Switches for NetWare Installation

Switch	Description
DSREMOVE	Allows absolute removal of DS.
R	Allows license replacement.

Switches Helpful for Install Script Writers

Switch	Description
DELAY	Wait until execution of AUTOEXEC.NCF is complete before activating screen.
NOSTATUS	Suppress status bar display in batch mode.
A=	NNNNNNNN:OOOOOOOOOOOO:SSSS or XXX.XXX.XXX source path IPX address: N hex network (8 chars): O hex node (12 chars): S hex socket source path IP address: XXX decimal value (1-3 chars)
B=	Batch file spec.
D=	Destination path in DOS for SERVER.EXE, etc.
E=	Error file spec.
O=	Overwrite existing files flag; 1: always, 2: never overwrite.
S=	Source path DOS specifier.
W=	Overwrite newer files flag; 1: always, 2: never overwrite.

Other Switches

Switch	Description
MDEBUG	Memory debug.
TRANSPORT	Transport layer type. (IPX is the default). IPX TCP UDP
C=	Source path remote context.
DS=	Specifies that NDS authentication will be used. If command is not present, the connection is made through the bindery.
F=	Front end flag. Q simplified mode T calculate file set totals V suppressed delayed init (DELAY) X allow more DS options
K=	Default startup.ncf file spec.
L=	Mode of installation.
N=	Source path remote server spec.
P=	Source path remote user password.
U=	Source path remote user name.
Z=	Source path remote tree.

NetWare 4.1 Remote Installation Wrapper

You can use NetWare installation to remotely install a product that was not originally intended for remote installation.

- 1** Create a wrapper script that copies the associated files to the server before executing PINSTALL.NLM.

Make sure the system volume is large enough to contain the scratch files, even in local install cases.

In the example below, the directory layout is as follows on the diskette:

\ (root)

 PINSTALL.IPS
 PINSTALL.NLM
 other files...

The contents of file PINSTALL.IPS appears as follows:

```
command icmd
getpath dest, 1, 'sys:system\\tmp', "
copyfile 0, 0, 0, 0, 0, NWSRC, '*.*', "", dest, "", "
; Additional copyfile commands might be needed to copy all diskettes
; See filedata.doc for details.
nlmexec 1, 'sys:system\\tmp\\pinstall'
erasefile 0, dest, "", "
```

PINSTALL.IPS script causes ICMD.NLM to be loaded. A path variable *dest* is set, all files are copied to that location, PINSTALL.NLM is executed, then the files are erased.

- 2** Load INSTALL.NLM.
- 3** Click Product Options > Install a Product Not Listed.
- 4** Press F3.
- 5** Enter the remote path:

server_name\vol_name:path

NetWare Installation Command Version Availability

The following tables list the available NetWare installation and external installation commands.

NetWare Install Commands

Command	NetWare 4.10	NetWare 4.11	NetWare for Small Business	NetWare 5 and NetWare 6
@CDName	X	X	X	X
@DeletePartition	X	X	X	X
@Driver	X	X	X	X
@FileSet	X	X	X	X
@IncludeFile	X	X	X	X
@MessageFile	X	X	X	X
@Other	X	X	X	X
@StartAppObject			X	
@StartSchemaMod		X	X	X
@SyntaxVersion	X	X	X	X
@TimeZone	X	X	X	X
@TranslateModule	X	X	X	X
@Version	X	X	X	X
Command	X	X	X	X
CopyDriverToServer	X	X	X	X
CopyDriverToStartup	X	X	X	X
CopyToServer	X	X	X	X
CopyToStartup	X	X	X	X

Command	NetWare 4.10	NetWare 4.11	NetWare for Small Business	NetWare 5 and NetWare 6
Exec	X	X	X	X
ProductRecord	X	X	X	X
RegisterLanguage	X	X	X	X
SaveLanguageFile	X	X	X	X
Spawn	X	X	X	X

NetWare External Install Commands

Command	Version of ICMD.NLM			
	2.00	2.18	3.20	3.25
Activate		X	X	X
AppendFile	X	X	X	X
CheckFile		X	X	X
Config	X	X	X	X
Console	X	X	X	X
CopyFile	X	X	X	X
CopyFloppyImage	X	X	X	X
Delay	X	X	X	X
DiskReset	X	X	X	X
Display_Text_File				X
Display	X	X	X	X
DSInst	X	X	X	X
EditNCF			X	X
EditNCF_Addline			X	X

Command	Version of ICMD.NLM			
	2.00	2.18	3.20	3.25
EditNCF_Keystings			X	X
EraseFile	X	X	X	X
ExtractVersionNumbers			X	X
GetDOSServer			X	X
GetPath	X	X	X	X
Goto		X	X	X
GotolfEqual		X	X	X
GotolfNEqual		X	X	X
GotolfGreater		X	X	X
GotolfLess		X	X	X
GotolfGrEqual		X	X	X
GotolfLsEqual		X	X	X
Is_NLM_Active				X
Label		X	X	X
LangVar	X	X	X	X
Menu		X	X	X
NLMExec	X	X	X	X
NLMExec_IO			X	X
Partitions	X	X	X	X
Quit				X
ReadProductRecord			X	X
Read_Var_File				X

Command	Version of ICMD.NLM			
	2.00	2.18	3.20	3.25
SetDir	X	X	X	X
SetDOSServer			X	X
SetLConfigLang	X	X	X	X
SetVar	X	X	X	X
SgotolfEqual		X	X	X
SgotolfNEqual		X	X	X
SgotolfGreater		X	X	X
SgotolfLess		X	X	X
SgotolfGrEqual		X	X	X
SgotolfLsEqual		X	X	X
SpaceCheck	X	X	X	X
SrchNCF			X	X
ValueAdd	X	X	X	X
ValueSet	X	X	X	X
Volumes	X	X	X	X
Write_Var_File				X