


	A	B	C	D	E	F	G	H	I
1									
2									
3	<div> <div> Vertica System Requirements ZENworks 2020 October 2019 </div> <div>  </div> </div>								
4									
5									
6									
7									
8									
9	S.No	No. of Devices in Zone	No. Of Admins concurrently using Dashboards	Memory Reserved for Vertica in Appliance	Overall Configuration for Appliance	No. of CPU Cores	Reccommended Size of Hard Disk	No. of Nodes in Vertica Cluster	No. of Nodes in Kafka Cluster
10	1	20K devices	2	12 GB RAM	16-24 GB RAM	6	500 GB	3	3
11	2	20K devices	5	16 GB RAM	32-64 GB RAM	8	500 GB	3	3
12	3	20K devices	10	32 GB RAM	64 GB RAM	16	500 GB	3	3
13	4	40K devices	5	16 GB RAM	32-64 GB RAM	8	750 GB	3	3
14	5	40K devices	10	32 GB RAM	64 GB RAM	16	750 GB	3	3
15	6	40K devices	20	64 GB RAM	64-96 GB RAM	32	750 GB	3	3
16	7	100K devices	5	16 GB RAM	32-64 GB RAM	8	1.5 TB	3	3
17	8	100K devices	10	32 GB RAM	64 GB RAM	16	1.5 TB	3	3
18	9	100K devices	20	64 GB RAM	64-96 GB RAM	32	1.5 TB	3	3
19									
20	Legal Notice								
21	For information about legal notices, trademarks, disclaimers, warranties, export and other use restrictions, U.S. Government rights, patent policy, and FIPS compliance, see https://www.novell.com/company/legal/ .								
22	© Copyright 2008 - 2019 Micro Focus or one of its affiliates. The only warranties for products and services of Micro Focus and its affiliates and licensors ("Micro Focus") are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Micro Focus shall not be liable for technical or editorial errors or omissions contained herein. The information contained herein is subject to change without notice.								
23									