

Novell ZENworks 7.2 Linux Management with Interim Release 1

August 23, 2007

1 Overview

The issues included in this document were identified in Novell® ZENworks® 7.2 Linux Management with Interim Release 1 (IR1).

For installation instructions, see the *Novell ZENworks 7.2 Linux Management Installation Guide* (<http://www.novell.com/documentation/zlm72/lm7install/data/front.html>).

For administration concepts and tasks, see the *Novell ZENworks 7.2 Linux Management Administration Guide* (<http://www.novell.com/documentation/zlm72/lm7admin/data/front.html>).

2 Known Issues

This section contains information about the issues that might occur when you install and use ZENworks 7.2 Linux Management with IR1.

2.1 Installation

This section contains information about the issues that might occur when you install ZENworks Linux Management.

2.1.1 The install fails on a RHEL4 AS 64-bit server if two NICs are present

255955

The installation fails on Red Hat* Enterprise Linux 4 (RHEL4) 64-bit and the `zlm-config` file indicates that the server requires a static IP or permanent DHCP address for the ZENworks Server.

Workaround: Launch `system-config-network`, delete the inactive NIC (eth1), then restart `zlm-config`. ZENworks Linux Management should install successfully.

2.1.2 RHEL5 64-bit (x86_64) is not supported as a managed device

299705 {{Newly added for IR1}}

RHEL5 64-bit (x86_64) is not supported as a managed device. Hence, the installation of the ZENworks Linux Management Agent on RHEL5 64-bit fails even though the status of the device is displayed as *Enabled* in ZENworks Control Center (*Configuration > Platforms*).

2.1.3 Installing the ZENworks Server software on a device configured with DHCP results in an eDirectory error

If you are installing to a device that is configured with DHCP, you might encounter the following eDirectory error in `zlm-config`:

```
eDir failed to start properly. Please ensure that this machine is configured with a static IP or permanently-leased DHCP Address.
```

Workaround: See “[Installing a ZENworks Server on a Device Configured with DHCP](#)” in the *Novell ZENworks 7.2 Linux Management Installation Guide*.

2.2 Upgrade

This section contains information about the issues that might occur when you upgrade ZENworks 7.2 Linux Management from a previous release.

2.2.1 Upgrading the Novell Linux Desktop 9 managed device from ZENworks 7 Linux Management with IR1 to ZENworks 7.2 Linux Management with IR1 by using upgrade bundles might fail

300098 {{Newly added for IR1}}

If you try to upgrade the Novell Linux Desktop 9 (NLD 9) managed device from ZENworks 7 Linux Management with IR1 to ZENworks 7.2 Linux Management with IR1 by using upgrade bundles, the upgrade might hang.

Workaround: Manually upgrade the NLD 9 managed device from ZENworks 7 Linux Management with IR1 to ZENworks 7.2 Linux Management with IR1 by using the *Novell ZENworks 7.2 Linux Management with Interim Release 1 Agent* CD. For detailed information on how to manually upgrade the managed device, see the *Novell ZENworks 7.2 Linux Management Installation Guide*.

2.2.2 The ZENworks Linux Management server might hang when the schema is upgraded from ZENworks 7 Linux Management with IR1 to ZENworks 7.2 Linux Management with IR1

293318 {{Newly added for IR1}}

If the status of the database is `Idle in Transaction`, the ZENworks Linux Management server might hang when the schema is upgraded from ZENworks 7 Linux Management with IR1 to ZENworks 7.2 Linux Management with IR1.

Workaround: Restart the database before upgrading to ZENworks 7.2 Linux Management with IR1.

2.2.3 The `ostargets.xml` file is not updated on the ZENworks Secondary Server after the server is upgraded from ZENworks 7 Linux Management with IR 1 to ZENworks 7.2 Linux Management with IR1

296791 {{Newly added for IR1}}

Workaround: After upgrading the ZENworks Secondary Server from ZENworks 7 Linux Management with IR 1 to ZENworks 7.2 Linux Management with IR1:

- 1 Delete `ostargets.xml` from ZENworks Secondary Server by executing `rm /var/opt/novell/zenworks/lib/www/ostargets.xml` at the server console prompt.

- 2 Copy `var/opt/novell/zenworks/lib/www/ostargets.xml` from the ZENworks Primary Server to `/var/opt/novell/zenworks/lib/www` on the ZENworks Secondary Server.
- 3 On the ZENworks Secondary Server, change the ownership of `ostargets.xml` to `zenworks` by executing `chown zenworks:zenworks /var/opt/novell/zenworks/lib/www/ostargets.xml` at the server console prompt.

2.3 ZENworks Database

This section contains information about the issues that might occur when you use the ZENworks database.

2.3.1 Unable to use `dbrestore` to restore the ZENworks database installed on a RHEL device

256603

Using the `zlm_dbrestore.sh` script to restore the ZENworks database installed on a RHEL device might fail.

Workaround: To resolve this issue, see the *Novell ZENworks 7.2 Linux Management Troubleshooting Guide*.

2.4 Package Management

This section contains information about the issues that might occur when you use the Package Management features of ZENworks Linux Management.

2.4.1 Wildcard characters do not work when executing a `bundle-list` command from `zman`

249150

The use of wildcard characters using the `bundle-list (bl)` command to list bundles is not currently supported.

2.4.2 A bundle is installed even when the post-distribution script fails

246169

Currently, a bundle is successfully installed even though a post-distribution script fails.

2.4.3 After a specific version of the bundle is installed on a device, changes to the deployment or installation schedule of the bundle are ignored for subsequent versions

252038

When a new bundle is associated to a device on a particular schedule, the bundle is deployed or installed based on the schedule configured. However, when the bundle is modified and a newer version is deployed, any changes to the schedule do not take effect. The newer version of the bundle is installed on the next refresh.

Workaround: None.

2.4.4 Some pattern, patch, and product rug commands are not supported

A few pattern, patch, and product `rug` commands are not supported on SLES 9, RHEL, and Novell Linux Desktop.

2.4.5 Package Update shows an incorrect status when a bundle is assigned to a server or workstation group

255611

Workaround: None.

2.4.6 An incorrect message is displayed on the secondary server on bundle creation as well as content replication

256596

The following message is displayed on the secondary server on successful creation of the bundle as well as content replication: "Cannot deploy this version because one or more packages have been deleted".

Workaround: Ignore the message.

2.4.7 Unable to remove a bundle installed on a managed device if zmd goes to sleep or is restarted

230852/222883

Workaround: Do one of the following on the managed device:

- ♦ Manually remove each package from the bundle using the `rug rm package_name` command.
- ♦ Stop `zmd`, delete `/var/opt/novell/zenworks/lib/zmd/system-catalog`, and restart `zmd`.

2.4.8 Bundles are deployed and installed immediately when the managed device is refreshed, even though they are scheduled to be deployed and installed at a later time

301301 {{Newly added for IRI}}

Even though you can schedule to deploy and install bundles on the managed device at a specific time, date, or event through ZENworks Control Center, the bundles are deployed and installed immediately when the managed device is refreshed.

Workaround: None.

2.5 Policy Management

This section contains information about the issues that might occur when you use the Policy Management features of ZENworks Linux Management.

2.5.1 SUSE Linux Enterprise Desktop policy issues

If you configure the SUSE Linux Enterprise Desktop policy for a SLED 10 managed device, you might encounter the following issues:

- ♦ [257616](#)The *Disable Launcher Creation* option does not work.
- ♦ [257325](#)If you try to remove an option that is selected in the *Show* drop-down list of the main menu file area, the main menu fails to appear. [257335](#)Also, if you try to unassign the policy from the managed device, the main menu still fails to appear.

Workaround: If the main menu fails to appear on unassigning the policy:

- a. Ensure that the policy is removed from the device by refreshing the managed device, and relogging into the device.
- b. On the managed device, right-click the panel, click *Add to Panel*, select *Main Menu* from the *Add to Panel* list, then click *Add*.

2.5.2 The previous background settings of the SLED 10 managed device are not restored after the SLED policy is unenforced

[237800](#)

On a SLED 10 managed device, if you unenforce the SLED policy in which the background image filename is configured, the previous background settings of the device are not restored.

Workaround: Log in to the managed device again.

2.5.3 The system area of the SLED 10 SP1 managed device disappears when you try to remove the system menus by using the SLED policy

[300273](#) {{newly added for IR1}}

If you enforce the SLED policy that is configured to remove the system menus from the system area, the system area on the SLED 10 SP1 managed device disappears.

Workaround: Remove the settings from the SLED policy and reassign the policy to the SLED 10 SP1 managed device.

2.6 Imaging

This section contains information about the issues that might occur when you use the Imaging features of ZENworks Linux Management.

2.6.1 After installing ZENworks Linux Management on a server, some image safe data is missing or incorrect

[251940](#)

If you take an image of a server just after installing ZENworks Linux Management (that is, before `zislx-start` has a chance to run again at boot), the image is restored with an incorrect network configuration and hostname.

Workaround: After completing the server installation, execute `/etc/init.d/novell-zislx start`.

This issue does not affect installation of the ZENworks Agent on a managed device.

2.6.2 The imaging server does not support double-byte characters in the name of the image file

121447

The Imaging engine does not support double-byte characters in image filenames. The ZENworks Control Center allows you to enter a double-byte character, but the Imaging Server does not recognize it. Therefore, do not use double-byte characters in the names of image files.

2.6.3 zislrx fails to shut down on RHEL 3 devices

158421

On Red Hat Enterprise Linux 3 (RHEL 3) devices, using the `/etc/init.d/novell-zislrx stop` command fails to shut the service down. At some later time, the device then fails to respond to a soft reboot, and must be cold-booted.

The error message displayed when running `/etc/init.d/novell-zislrx stop` is incorrect, because RHEL 3 does not follow LSB standards.

Workaround: Do not use the `/etc/init.d/novell-zislrx stop` command. Normally, you would not run this command, because when `/etc/init.d/novell-zislrx` is run from either a bash prompt or at boot-up, it runs once then stops itself.

2.6.4 "Error: Could not create linux symbolic link" when restoring extracted add-on image

121403

The use of a symbolic link is not supported in add-on images if the link's location does not exist on the device where the add-on image is extracted.

2.6.5 Not able to get into the utility partition after applying a configuration bundle on a Dell PE700 device

158027

The Dell* utility partition relies on its version of the MBR (master boot record) to function correctly. Grub also uses the MBR for its boot loader. If you install the Dell utility partition, then install the Linux* operating system, the Dell version of the MBR is overwritten by the grub version. Instructions to remedy this problem are found in "[Creating Dell Configuration Bundles](#)" in the *Novell ZENworks 7.2 Linux Management Administration Guide*.

However, the instructions do not work for Dell PE700 devices. For Dell PE700 devices, there is not workaround.

2.7 Inventory

This section contains information about the issues that might occur when you use the Inventory features of ZENworks Linux Management.

2.7.1 Hardware Inventory fails to report some information

- ♦ A hardware inventory currently does not report some items, such as power supply for any type of device. For Red Hat machines, items such as floppy and monitor are not recognized.
- ♦ On SLES 9, Novell Linux Desktop, and Open Enterprise Server managed devices, the hardware probe using the hwinfo utility might unload the lp module and consequently remove the printer device.

Workaround: Download and install the updates for the hwinfo utility. For detailed information on how to obtain the updates, see the [Novell Support Web site \(http://support.novell.com/techcenter/psdb/625a8580c15ecc6e9aad85d05772ae67.html\)](http://support.novell.com/techcenter/psdb/625a8580c15ecc6e9aad85d05772ae67.html).

2.7.2 CPU-based registration rules might fail for a few Intel Pentium processors

If you create a CPU-based registration rule to filter Intel* Pentium* processors for registering the managed device to the server, the Inventory Scanner utility (hwinfo) captures the CPU model name as "Pentium(R) 4 processor 2800 MHz" instead of "Intel(R) Pentium(R) 4 CPU 2.80GHz" for some machines; the prefix Intel is omitted. Consequently, the registration of the device to the server might fail.

Workaround: None.

2.8 Remote Management

This section contains information about the issues that might occur when you use the Remote Management features of ZENworks 7.2 Linux Management.

2.8.1 A grey screen is displayed when you start the Remote Login operation

294738

When you start the Remote Login operation on a managed device, the launched session shows only a grey screen with an X cursor because XDMCP is not enabled on the managed device.

Workaround: On the managed device, do the following:

- 1 Manually enable XDMCP by executing the `novell-rm-fixrl.sh` script from a console session as mentioned below:
 - ♦ **On SLES 10 and SLED 10:** Execute `/usr/bin/novell-rm-fixrl.sh -dm gdm -cf /etc/opt/gnome/gdm/gdm.conf enable`.
 - ♦ **On SLES 9 and Novell Linux Desktop:** Execute `/opt/novell/zenworks/bin/novell-rm-fixrl.sh -dm gdm -cf /etc/opt/gnome/gdm/gdm.conf enable`.
 - ♦ **On RHEL:** Execute `/opt/novell/zenworks/bin/novell-rm-fixrl.sh -dm gdm -cf /etc/X11/gdm/gdm.conf enable`.
- 2 Start the Remote Login operation.

2.8.2 The Remote Management -VNC applet sometimes hangs when starting a remote management session

158590

When starting a remote management session, the Remote Management -VNC applet randomly hangs.

Workaround: Stop and restart all running browser sessions, then retry the remote management session.

3 Documentation Conventions

In this documentation, a greater-than symbol (>) is used to separate actions within a step and items in a cross-reference path.

A trademark symbol (® , TM, etc.) denotes a Novell trademark; an asterisk (*) denotes a third-party trademark.

4 Legal Notices

Novell, Inc. makes no representations or warranties with respect to the contents or use of this documentation, and specifically disclaims any express or implied warranties of merchantability or fitness for any particular purpose. Further, Novell, Inc. reserves the right to revise this publication and to make changes to its content, at any time, without obligation to notify any person or entity of such revisions or changes.

Further, Novell, Inc. makes no representations or warranties with respect to any software, and specifically disclaims any express or implied warranties of merchantability or fitness for any particular purpose. Further, Novell, Inc. reserves the right to make changes to any and all parts of Novell software, at any time, without any obligation to notify any person or entity of such changes.

Any products or technical information provided under this Agreement may be subject to U.S. export controls and the trade laws of other countries. You agree to comply with all export control regulations and to obtain any required licenses or classification to export, re-export, or import deliverables. You agree not to export or re-export to entities on the current U.S. export exclusion lists or to any embargoed or terrorist countries as specified in the U.S. export laws. You agree to not use deliverables for prohibited nuclear, missile, or chemical biological weaponry end uses. Please refer to <http://www.novell.com/info/exports/> (<http://www.novell.com/info/exports/>) for more information on exporting Novell software. Novell assumes no responsibility for your failure to obtain any necessary export approvals.

Copyright © 2007 Novell, Inc. All rights reserved. No part of this publication may be reproduced, photocopied, stored on a retrieval system, or transmitted without the express written consent of the publisher.

Novell, Inc. has intellectual property rights relating to technology embodied in the product that is described in this document. In particular, and without limitation, these intellectual property rights may include one or more of the U.S. patents listed at <http://www.novell.com/company/legal/patents> (<http://www.novell.com/company/legal/patents>) and one or more additional patents or pending patent applications in the U.S. and in other countries.

For Novell trademarks, see [the Novell Trademark and Service Mark list \(http://www.novell.com/company/legal/trademarks/tmlist.html\)](http://www.novell.com/company/legal/trademarks/tmlist.html).

All third-party trademarks are the property of their respective owners.